

# BR2300-FJD4

## BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

### Supported bill FJD 5, 7, 10, 20 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
Reject FJD 5 & 7	ON									
★ Accept FJD 5 & 7	OFF									
Reject FJD 10		ON								
★ Accept FJD 10		OFF								
Reject FJD 20			ON							
★ Accept FJD 20			OFF							
High Acceptance <small>(Note.3)</small>				ON						
★ High Security				OFF						
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 <small>(MDB Only)</small>					ON					
★ Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★ Normal						OFF	OFF			
Load Banknote to Recycle						ON	OFF			
Load Banknote to Stacker						OFF	ON			
Unload Banknote to Stacker						ON	ON			
★ ccTalk								ON	OFF	
ccTalk <small>(Note.1)</small>								OFF	ON	
★ MDB Mode								OFF	OFF	
★ ICT-BC Mode								ON	ON	
ccTalk	MDB Mode		ICT-BC Mode							
★ Encryption MODE	★ Virtual MDB Recycler Function (Note.2)		Connect with MDB Connector							ON
Decrypt MODE	Standard MDB Recycler Function		★ Connect with RS232 Connector							OFF

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2 Recycled Banknote represents virtual MDB coin type.

Note.3: High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Note.4: Calibration card is needed.

## Currency Assign Data

Interface Bill value	ccTalk	ICT-BC	MDB
BV1	FJD 5	FJD 5	FJD 5
BV2	FJD 7	FJD 7	FJD 7
BV3	FJD 10	FJD 10	FJD 10
BV4	FJD 20	FJD 20	FJD 20