

## BR2300-MYR3

### BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill MYR 10, 20, 50 3 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject MYR 10	ON									
	Accept MYR 10	OFF									
	Reject MYR 20		ON								
★	Accept MYR 20		OFF								
	Reject MYR 50			ON							
★	Accept MYR 50			OFF							
	High Acceptance (Note.3)				ON						
★	High Security				OFF						
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	(MDB only)				ON					
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★	Normal						OFF	OFF			
	Load Banknote to Recycle						ON	OFF			
	Load Banknote to Stacker						OFF	ON			
	Unload Banknote to Stacker						ON	ON			
★	ccTalk								ON	OFF	
	ccTalk (Note.1)								OFF	ON	
★	MDB Mode								OFF	OFF	
★	ICT-BC Mode								ON	ON	
	ccTalk	MDB Mode				ICT-BC Mode					
★	Encryption MODE	★ Virtual MDB Recycler Function (Note.2)				Connect with MDB Connector				ON	
	Decrypt MODE	Standard MDB Recycler Function				★ Connect with RS232 Connector				OFF	

#### ★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2: Recycled Banknote represents virtual MDB coin type.

Note.3: High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor

Note.4: Calibrate card is needed.

## BR2300-MYR3 (MDB/ICT-BC/ccTalk)

### Currency Assign Data

Interface Bill value	ccTalk	ICT-BC	MDB	Recycler banknote inventory	
BV1					
BV2					
BV3					
BV4	MYR 10	MYR 10	MYR 10	MYR 10	40 pcs
BV5	MYR 50	MYR 50	MYR 50	MYR 50	40 pcs
BV6					
BV7	MYR 20	MYR 20	MYR 20	MYR 20	40 pcs