

BR2300-MYR6

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill MYR 1, 5, 10, 20, 50, 100 6 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject MYR 1 & 5 & 10	ON									
	Accept MYR 1 & 5 & 10	OFF									
	Reject MYR 20		ON								
★	Accept MYR 20		OFF								
	Reject MYR 50 & 100			ON							
★	Accept MYR 50 & 100			OFF							
	High Acceptance (Note.3)			ON							
★	High Security			OFF							
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	(MDB only)				ON					
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★	Normal					OFF	OFF				
	Load Banknote to Recycle					ON	OFF				
	Load Banknote to Stacker					OFF	ON				
	Unload Banknote to Stacker					ON	ON				
★	ccTalk							ON	OFF		
	ccTalk (Note.1)							OFF	ON		
★	MDB Mode							OFF	OFF		
★	ICT-BC Mode							ON	ON		
	ccTalk	MDB Mode				ICT-BC Mode					
★	Encryption MODE	Virtual MDB Recycler Function (Note.2)				Connect with MDB Connector				ON	
	Decrypt MODE	Standard MDB Recycler Function				Connect with RS232 Connector				OFF	

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2: Recycled Banknote represents virtual MDB coin type.

Note.3: High acceptance mode will increasing accepting rate, however, it will reduce the security level of BillAcceptor

Note.4: Calibrate card is needed.

BR2300-MYR6 (MDB/ICT-BC/ccTalk)

Currency Assign Data

Interface Bill value	ccTalk	ICT-BC	MDB	Recycler banknote inventory	
BV1	MYR 1	MYR 1	MYR 1	MYR 1	45 pcs
BV2					0 pcs
BV3	MYR 5	MYR 5	MYR 5	MYR 5	40 pcs
BV4	MYR 10	MYR 10	MYR 10	MYR 10	40 pcs
BV5	MYR 50	MYR 50	MYR 50	MYR 50	40 pcs
BV6	MYR 100	MYR 100	MYR 100	MYR 100	40 pcs
BV7	MYR 20	MYR 20	MYR 20	MYR 20	40 pcs