

L77F/PL77-INR7

L77F/PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill INR 5, 10, 20, 50, 100, 200, 500 7bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / INR 5 & 10 (Note.2)	OFF	OFF	OFF							
2 Pulses / INR 5 & 10 (Note.2)	OFF	OFF	ON							
3 Pulses / INR 5 & 10 (Note.2)	OFF	ON	OFF							
4 Pulses / INR 5 & 10 (Note.2)	OFF	ON	ON							
5 Pulses / INR 5 & 10 (Note.2)	ON	OFF	OFF							
10 Pulses / INR 5 & 10 (Note.2)	ON	OFF	ON							
20 Pulses / INR 5 & 10 (Note.2)	ON	ON	OFF							
100 Pulses / INR 5 & 10 (Note.2)	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept INR 5 (Note.2)						ON				
Reject INR 5 (Note.2)						OFF				
★ Accept INR 10 & 20 & 50							ON			
Reject INR 10 & 20 & 50							OFF			
★ Accept INR 100 & 200								ON		
Reject INR 100 & 200								OFF		
★ Accept INR 500									ON	
Reject INR 500									OFF	
High Security Mode										ON
★ Medium Security Mode										OFF

★ Manufacture setting

Note : (1) Please reset the bill acceptor after set the dip switch.

(2) ** Pulse Mode:

When Dip 6 is OFF,One Pulse per INR 10.

When Dip 6 is ON,One Pulse per INR 5.

L77F/PL77-INR7 (Pulse/ICT104U/MDB/ICT104V)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U ICT104V	Pulse		MDB	
		When Dip 6 is OFF	When Dip 6 is ON	When Dip 6 is OFF	When Dip 6 is ON
BV1	INR 5		INR 5	INR 10	INR 5
BV2	INR 10	INR 10	INR 10	INR 20	INR 10
BV3	INR 20	INR 20	INR 20	INR 50	INR 20
BV4	INR 50	INR 50	INR 50	INR 100	INR 50
BV5	INR 100	INR 100	INR 100	INR 200	INR 100
BV6	INR 500	INR 200	INR 200	INR 500	INR 200
BV7		INR 500	INR 500		INR 500
BV8					
BV9	INR 200				

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
★ MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting