

## L77F-PHP6

### L77F DIP SWITCHES SETTING : 1(Pulse/ccTalk/ICT104)

Supported bill ₱ 20, 50, 100, 200, 500, 1000 6bills.

|   | FUNCTION                                  | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|---|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ | 1 Pulse / ₱ 10                            | OFF | OFF | OFF |     |     |     |     |     |     |      |
|   | 2 Pulse / ₱ 10                            | OFF | OFF | ON  |     |     |     |     |     |     |      |
|   | 3 Pulse / ₱ 10                            | OFF | ON  | OFF |     |     |     |     |     |     |      |
|   | 4 Pulse / ₱ 10                            | OFF | ON  | ON  |     |     |     |     |     |     |      |
|   | 5 Pulse / ₱ 10                            | ON  | OFF | OFF |     |     |     |     |     |     |      |
|   | 10 Pulse / ₱ 10                           | ON  | OFF | ON  |     |     |     |     |     |     |      |
|   | 20 Pulse / ₱ 10                           | ON  | ON  | OFF |     |     |     |     |     |     |      |
|   | 100 Pulse / ₱ 10                          | ON  | ON  | ON  |     |     |     |     |     |     |      |
|   | Fast output Pulse<br>Lo= 50ms<br>Hi=100ms |     |     |     | ON  |     |     |     |     |     |      |
| ★ | Slow output Pulse<br>Lo= 50ms<br>Hi=300ms |     |     |     | OFF |     |     |     |     |     |      |
|   | Inhibit level Active Low                  |     |     |     | ON  |     |     |     |     |     |      |
| ★ | Inhibit level Active High                 |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept ₱ 20                               |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject ₱ 20                               |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept ₱ 50                               |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject ₱ 50                               |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept ₱ 100 & 200                        |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject ₱ 100 & 200                        |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept ₱ 500                              |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject ₱ 500                              |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept ₱ 1000                             |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject ₱ 1000                             |     |     |     | OFF |     |     |     |     |     |      |

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

## L77F-PHP6(Pulse/ccTalk/ICT104)

### DIP SWITCHES SETTING : 2(Pulse)

|   | FUNCTION          | SW1 | SW2 | SW3 | SW4 |
|---|-------------------|-----|-----|-----|-----|
| ★ | Pulse Normal High | ON  |     |     |     |
|   | Pulse Normal Low  | OFF |     |     |     |
| ★ | Pulse Mode        |     | ON  | OFF |     |
|   | ccTalk Interface  |     | OFF | OFF |     |
|   | ICT104 Mode       |     | ON  | ON  |     |
|   | Reserved          |     | OFF | ON  |     |
| ★ | Reserved          |     |     |     | ON  |
|   |                   |     |     |     | OFF |

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ccTalk)

|   | FUNCTION   | SW1 | SW2 | SW3 | SW4 |
|---|--|-----|-----|-----|-----|
|   | 8-bit checksum   | ON  |     |     |     |
| ★ | CRC 16-bit checksum  | OFF |     |     |     |
|   | Pulse Mode   |     | ON  | OFF |     |
| ★ | ccTalk Interface   |     | OFF | OFF |     |
|   | ICT104 Mode  |     | ON  | ON  |     |
|   | ccTalk Parameters Restore Switch<br>Please see "Note" for detail |     | OFF | ON  |     |
| ★ | Encryption Mode  |     |     |     | ON  |
|   | Decrypt Mode   |     |     |     | OFF |

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

### DIP SWITCHES SETTING : 2(ICT104)

|   | FUNCTION         | SW1 | SW2 | SW3 | SW4 |
|---|------------------|-----|-----|-----|-----|
| ★ | Reserved         | ON  |     |     |     |
|   |                  | OFF |     |     |     |
|   | Pulse Mode       |     | ON  | OFF |     |
|   | ccTalk Interface |     | OFF | OFF |     |
| ★ | ICT104 Mode      |     | ON  | ON  |     |
|   | Reserved         |     | OFF | ON  |     |
| ★ | Reserved         |     |     |     | ON  |
|   |                  |     |     |     | OFF |

★ Manufacture setting

### Currency Assign Data

| Interface<br>Bill value | ICT    | ccTalk | Pulse  |
|-------------------------|--------|--------|--------|
| BV1                     | ₱ 20   | ₱ 20   | ₱ 20   |
| BV2                     | ₱ 50   | ₱ 50   | ₱ 50   |
| BV3                     | ₱ 100  | ₱ 100  | ₱ 100  |
| BV4                     | ₱ 500  | ₱ 200  | ₱ 200  |
| BV5                     | ₱ 1000 | ₱ 500  | ₱ 500  |
| BV6                     | ₱ 200  | ₱ 1000 | ₱ 1000 |