

L77F/PL77-GEL6

L77F/PL77 Option Switch Settings : 1(Pulse/RS232 A0/ccNet/ICT104U)

Supported bill Lari 5, 10, 20, 50, 100, 200 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Lari 5	OFF	OFF	OFF							
2 Pulses / Lari 5	OFF	OFF	ON							
3 Pulses / Lari 5	OFF	ON	OFF							
4 Pulses / Lari 5	OFF	ON	ON							
5 Pulses / Lari 5	ON	OFF	OFF							
10 Pulses / Lari 5	ON	OFF	ON							
20 Pulses / Lari 5	ON	ON	OFF							
100 Pulses / Lari 5	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Lari 5 & 10						ON				
Reject Lari 5 & 10						OFF				
★ Accept Lari 20 & 50							ON			
Reject Lari 20 & 50							OFF			
★ Accept Lari 100								ON		
Reject Lari 100								OFF		
★ Accept Lari 200									ON	
Reject Lari 200									OFF	
Simulation BillBox Has Been Removed										ON
★ Default										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

Currency Assign Data

Interface	RS232 A0	Pulse	ccNet	ICT104U
BV3	Lari 5	Lari 5	Lari 5	Lari 5
BV4	Lari 10	Lari 10	Lari 10	Lari 10
BV5	Lari 20	Lari 20	Lari 20	Lari 20
BV6	Lari 50	Lari 50	Lari 50	Lari 50
BV7	Lari 100	Lari 100	Lari 100	Lari 100
BV8	Lari 200	Lari 200	Lari 200	Lari 200

Appendix

L77F/PL77-GEL6(Pulse/RS232 A0/ccNet/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
RS232 A0 Mode		ON	ON	
★ Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
★ RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
★ Reserved				ON
Reserved				OFF

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Lari 1
2	Lari 2
3	Lari 5
4	Lari 10
5	Lari 20
6	Lari 50
7	Lari 100
8	Lari 200
9	Reserved

DIP SWITCHES SETTING : 2(ccNet)

FUNCTION	SW1	SW2	SW3	SW4
★ Baud rate 19200	ON			
Baud rate 9600	OFF			
★ RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
★ ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
★ Reserved				ON
Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
★ ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
★ Reserved				ON
Reserved				OFF

★ Manufacture setting