

# L77F&PL77-THB5

## L77F&PL77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT10A/ICT104U)

Supported bill ₪ 20, 50, 100, 500, 1000

5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / ₪ 10	OFF	OFF	OFF							
	2 Pulse / ₪ 10	OFF	OFF	ON							
	3 Pulse / ₪ 10	OFF	ON	OFF							
	4 Pulse / ₪ 10	OFF	ON	ON							
	5 Pulse / ₪ 10	ON	OFF	OFF							
	10 Pulse / ₪ 10	ON	OFF	ON							
	20 Pulse / ₪ 10	ON	ON	OFF							
	100 Pulse / ₪ 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept ₪ 20 & 50						ON				
	Reject ₪ 20 & 50						OFF				
★	Accept ₪ 100							ON			
	Reject ₪ 100							OFF			
★	Accept ₪ 500								ON		
	Reject ₪ 500								OFF		
★	Accept ₪ 1000									ON	
	Reject ₪ 1000									OFF	
★	High Security										ON
	High Acceptance (Note.3)										OFF

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

(3)High acceptance mode will increase accepting rate, however, it will reduce the security level of Bill Acceptor.

## Currency Assign Data

Interface Bill value	ICT104U	Pulse	ICT10A
BV1	₪ 20	₪ 20	₪ 20
BV2	₪ 50	₪ 50	₪ 50
BV3	₪ 100	₪ 100	₪ 100
BV4	₪ 500	₪ 500	₪ 500
BV5	₪ 1000	₪ 1000	₪ 1000

# L77F&PL77-THB5 ( Pulse/ICT10A/ICT104U)

## DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		ON	ON	
	ICT10A Mode		OFF	ON	
	Reserved		OFF	OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Forth mode	ON			
	Normal	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		ON	ON	
	ICT10A Mode		OFF	ON	
	Reserved		OFF	OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(ICT10A)

	FUNCTION	SW1	SW2	SW3	SW4
★	Forth mode	ON			
	Normal	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		ON	ON	
★	ICT10A Mode		OFF	ON	
	Reserved		OFF	OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting