

## L77F/PL77-THB5

### L77F&PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccTalk)

Supported bill THB 20, 50, 100, 500, 1000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / THB 10	OFF	OFF	OFF							
	2 Pulse / THB 10	OFF	OFF	ON							
	3 Pulse / THB 10	OFF	ON	OFF							
	4 Pulse / THB 10	OFF	ON	ON							
	5 Pulse / THB 10	ON	OFF	OFF							
	10 Pulse / THB 10	ON	OFF	ON							
	20 Pulse / THB 10	ON	ON	OFF							
	100 Pulse / THB 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low (Nota.4)				ON						
★	Inhibit level Active High				OFF						
★	Accept THB 20 & 50				ON						
	Reject THB 20 & 50				OFF						
★	Accept THB 100				ON						
	Reject THB 100				OFF						
★	Accept THB 500				ON						
	Reject THB 500				OFF						
★	Accept THB 1000				ON						
	Reject THB 1000				OFF						
★	High Security				ON						
	High Acceptance (Nota.5)				OFF						

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

(4) External motor Command. (ICT ONLY)  
ON : Motor Command.  
OFF : Reserved.

(5) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

### Currency Assign Data

Interface Bill value	Pulse	ICT104U	ccTalk
BV1	20	20	20
BV2	50	50	50
BV3	100	100	100
BV4	500	500	500
BV5	1000	1000	1000

## Appendix

## L77F&PL77-THB5(Pulse/ICT104U/ccTalk)

### DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	ICT104U Mode		ON	ON	
★	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
★	8-bit checksum	ON			
	CRC 16-bit checksum	OFF			
	ICT104U Mode		ON	ON	
	Pulse Mode		ON	OFF	
★	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
	Encryption Mode				
★	Decrypt Mode				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Forth only	ON			
	Reserved	OFF			
★	ICT104U Mode		ON	ON	
	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Note: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.