

L77F/PL77-THB5

L77F&PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccTalk)

Supported bill THB 20, 50,100,500,1000 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / THB 10	OFF	OFF	OFF							
2 Pulse / THB 10	OFF	OFF	ON							
3 Pulse / THB 10	OFF	ON	OFF							
4 Pulse / THB 10	OFF	ON	ON							
5 Pulse / THB 10	ON	OFF	OFF							
10 Pulse / THB 10	ON	OFF	ON							
20 Pulse / THB 10	ON	ON	OFF							
100 Pulse / THB 10	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low				ON						
★ Inhibit level Active High				OFF						
★ Accept THB 20 & 50				ON						
Reject THB 20 & 50				OFF						
★ Accept THB 100				ON						
Reject THB 100				OFF						
★ Accept THB 500				ON						
Reject THB 500				OFF						
★ Accept THB 1000				ON						
Reject THB 1000				OFF						
★ High Security				ON						
High Acceptance <small>(Note.4)</small>				OFF						

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

(4) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Currency Assign Data

Interface Bill value	Pulse	ICT104U	ccTalk
BV1	20	20	20
BV2	50	50	50
BV3	100	100	100
BV4	500	500	500
BV5	1000	1000	1000

Appendix

L77F&PL77-THB5(Pulse/ICT104U/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
ICT104U Mode		ON	ON	
★ Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
★ 8-bit checksum	ON			
CRC 16-bit checksum	OFF			
ICT104U Mode		ON	ON	
Pulse Mode		ON	OFF	
★ ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ ICT104U Mode		ON	ON	
Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

Note: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.