

L77F-EUR6

L77F-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB)

Supported bill € 5, 10, 20, 50, 100, 200 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / € 5	OFF	OFF	OFF							
2 Pulses / € 5	OFF	OFF	ON							
3 Pulses / € 5	OFF	ON	OFF							
4 Pulses / € 5	OFF	ON	ON							
5 Pulses / € 5	ON	OFF	OFF							
10 Pulses / € 5	ON	OFF	ON							
20 Pulses / € 5	ON	ON	OFF							
100 Pulses / € 5	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept € 5						ON				
Reject € 5						OFF				
★ Accept € 10 & 20							ON			
Reject € 10 & 20							OFF			
★ Accept € 50								ON		
Reject € 50								OFF		
★ Accept € 100(2019) & 200(2019)									ON	
★ Reject € 100(2019) & 200(2019)									OFF	
★ Accept Normal										ON
Reject € 5(2002) & 10(2002)										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

L77F-EUR6(Pulse/ICT104U/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	MDB_EU
BV1	€ 5	€ 5	€ 5
BV2	€ 10	€ 10	€ 10
BV3	€ 20	€ 20	€ 20
BV4	€ 50	€ 50	€ 50
BV4	€ 100	€ 100	€ 100
BV4	€ 200	€ 200	€ 200

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting