

L77F/PL77-CHF4

L77F&PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccTalk)

Supported bill CHF 10, 20, 50, 100 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / CHF 10	OFF	OFF	OFF							
	2 Pulse / CHF 10	OFF	OFF	ON							
	3 Pulse / CHF 10	OFF	ON	OFF							
	4 Pulse / CHF 10	OFF	ON	ON							
	5 Pulse / CHF 10	ON	OFF	OFF							
	10 Pulse / CHF 10	ON	OFF	ON							
	20 Pulse / CHF 10	ON	ON	OFF							
	100 Pulse / CHF 10	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept CHF 10						ON				
	Reject CHF 10						OFF				
★	Accept CHF 20							ON			
	Reject CHF 20							OFF			
★	Accept CHF 50								ON		
	Reject CHF 50								OFF		
★	Accept CHF 100									ON	
	Reject CHF 100									OFF	
★	Reserve										ON
	Reserve										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

PL77/L77F-CHF4(Pulse/ICT104U/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ICT104U Mode		ON	ON	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
	Pulse Mode		ON	OFF	
★	ccTalk Interface		OFF	OFF	
	ICT104U Mode		ON	ON	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
★	ICT104U Mode		ON	ON	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	ccTalk
BV1	CHF 10	CHF 10	CHF 10
BV2	CHF 20	CHF 20	CHF 20
BV3	CHF 50	CHF 50	CHF 50
BV4	CHF 100	CHF 100	CHF 100