

PL77/L77F-EUR6

PL77/L77F DIP SWITCHES SETTING : 1(Pulse/ccTalk/ICT104U)

Supported bill EUR 5, 10, 20, 50, 100, 200 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / EUR 5	OFF	OFF	OFF							
	2 Pulse / EUR 5	OFF	OFF	ON							
	3 Pulse / EUR 5	OFF	ON	OFF							
	4 Pulse / EUR 5	OFF	ON	ON							
	5 Pulse / EUR 5	ON	OFF	OFF							
	10 Pulse / EUR 5	ON	OFF	ON							
	20 Pulse / EUR 5	ON	ON	OFF							
	100 Pulse / EUR 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept EUR 5				ON						
	Reject EUR 5				OFF						
★	Accept EUR 10 & 20				ON						
	Reject EUR 10 & 20				OFF						
★	Accept EUR 50				ON						
	Reject EUR 50				OFF						
	Accept EUR 100(2019) & 200(2019)				ON						
★	Reject EUR 100(2019) & 200(2019)				OFF						
★	Accept Normal				ON						
	Reject EUR 5(2002) & 10(2002)				OFF						

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

(4) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

PL77/L77F-EUR6(Pulse/ccTalk/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ICT104U Mode		ON	ON	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
★	8-bit checksum	ON			
	CRC 16-bit checksum	OFF			
★	Pulse Mode		ON	OFF	
★	ccTalk Interface		OFF	OFF	
	ICT104U Mode		ON	ON	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
★	ICT104U Mode		ON	ON	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	ccTalk
BV1	EUR 5	EUR 5	EUR 5
BV2	EUR 10	EUR 10	EUR 10
BV3	EUR 20	EUR 20	EUR 20
BV4	EUR 50	EUR 50	EUR 50
BV5	EUR100	EUR100	EUR100
BV6	EUR200	EUR200	EUR200