

PL77/L77F-UCD9(USD6+CAD3)

PL77/L77F DIP SWITCHES SETTING : 1(Pulse/ccTalk/ICT104U)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.
CAD 5, 10, 20 3bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / USD 1	OFF	OFF	OFF							
2 Pulse / USD 1	OFF	OFF	ON							
3 Pulse / USD 1	OFF	ON	OFF							
4 Pulse / USD 1	OFF	ON	ON							
5 Pulse / USD 1	ON	OFF	OFF							
10 Pulse / USD 1	ON	OFF	ON							
20 Pulse / USD 1	ON	ON	OFF							
100 Pulse / USD 1	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept USD 1 & 5						ON				
Reject USD 1 & 5						OFF				
★ Accept USD 10 & 20							ON			
Reject USD 10 & 20							OFF			
Accept USD 50 & 100								ON		
★ Reject USD 50 & 100								OFF		
★ Accept CAD 5 & 10 & 20									ON	
Reject CAD 5 & 10 & 20									OFF	
★ Accept USD + CAD										ON
Accept only CAD										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

PL77/L77F-UCD9(Pulse/ccTalk/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
ICT104U Mode		ON	ON	
Reserved		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
8-bit checksum	ON			
★ CRC 16-bit checksum	OFF			
Pulse Mode		ON	OFF	
★ ccTalk Interface		OFF	OFF	
ICT104U Mode		ON	ON	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
★ ICT104U Mode		ON	ON	
Reserved		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	ccTalk
BV1	USD 1	USD 1	USD 1
BV2	USD 5	USD 5	USD 5
BV3	USD 10	USD 10	USD 10
BV4	USD 20	USD 20	USD 20
BV5	USD 50	USD 50	USD 50
BV6	USD 100	USD 100	USD 100
BV7	CAD 5	CAD 5	CAD 5
BV8	CAD 10	CAD 10	CAD 10
BV9	CAD 20	CAD 20	CAD 20