

L83-AMD2

L83-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccTalk)

Supported bill AMD 1000, 2000 2bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / AMD 1000	OFF	OFF	OFF							
	2 Pulse / AMD 1000	OFF	OFF	ON							
	3 Pulse / AMD 1000	OFF	ON	OFF							
	4 Pulse / AMD 1000	OFF	ON	ON							
	5 Pulse / AMD 1000	ON	OFF	OFF							
	10 Pulse / AMD 1000	ON	OFF	ON							
	20 Pulse / AMD 1000	ON	ON	OFF							
	100 Pulse / AMD 1000	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept AMD 1000						ON				
	Reject AMD 1000						OFF				
★	Accept AMD 2000						ON				
	Reject AMD 2000						OFF				
★	Reserved							ON			
	Reserved							OFF			
★	Reserved								ON		
	Reserved								OFF		
★	Reserved									ON	
	Reserved									OFF	

★ Manufacture Default setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only for pulse mode.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L83-AMD2(Pulse/ICT104U/ccTalk)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Interface		ON	OFF	
	ICT104U Interface		ON	ON	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Interface		ON	OFF	
★	ICT104U Interface		ON	ON	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	CcTalk
BV1	AMD 1000	AMD 1000	AMD 1000
BV2	AMD 2000	AMD 2000	AMD 2000

Interface Settings: 2(ccTalk)

	INTERFACE	SW1	SW2	SW3	SW4
★	8-bit checksum	ON			
	CRC 16-bit checksum	OFF			
	Pulse Interface		ON	OFF	
	ICT104U Interface		ON	ON	
★	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting