

L83-IRR8

L83 DIP SWITCHES SETTING : 1(Pulse/ICT/MDB)

Supported bill Rial 500, 1000, 2000, 5000, 10000, 20000, 50000, 100000 8bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Rial 500	OFF	OFF	OFF							
	2 Pulse / Rial 500	OFF	OFF	ON							
	3 Pulse / Rial 500	OFF	ON	OFF							
	4 Pulse / Rial 500	OFF	ON	ON							
	5 Pulse / Rial 500	ON	OFF	OFF							
	10 Pulse / Rial 500	ON	OFF	ON							
	20 Pulse / Rial 500	ON	ON	OFF							
	100 Pulse / Rial 500	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept Rial 500 & 1000				ON						
	Reject Rial 500 & 1000				OFF						
★	Accept Rial 2000 & 5000				ON						
	Reject Rial 2000 & 5000				OFF						
★	Accept Rial 10000 & 20000				ON						
	Reject Rial 10000 & 20000				OFF						
★	Accept Rial 50000				ON						
	Reject Rial 50000				OFF						
★	Accept Rial 100000				ON						
	Reject Rial 100000				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L83-IRR8(Pulse/ICT/MDB)

DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
	Reserved				ON
★	Reserved				OFF

Interface Bill value	Pulse	ICT104	MDB_EU
BV1	Rial 500	Rial 500	Rial 500
BV2	Rial 1000	Rial 1000	Rial 1000
BV3	Rial 2000	Rial 2000	Rial 2000
BV4	Rial 5000	Rial 5000	Rial 5000
BV5	Rial 10000	Rial 10000	Rial 10000
BV6	Rial 20000	Rial 20000	Rial 20000
BV7	Rial 50000	Rial 50000	Rial 50000
BV8	Rial 100000	Rial 100000	Rial 100000

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT Interface		OFF	ON	
★	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting