

L83-KES5

L83 Option Switch Settings : 1(Pulse/RS232 A0/ccTalk/ICT104U)

Supported bill KES 50, 100, 200, 500, 1000 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / KES 50	OFF	OFF	OFF							
2 Pulses / KES 50	OFF	OFF	ON							
3 Pulses / KES 50	OFF	ON	OFF							
4 Pulses / KES 50	OFF	ON	ON							
5 Pulses / KES 50	ON	OFF	OFF							
10 Pulses / KES 50	ON	OFF	ON							
20 Pulses / KES 50	ON	ON	OFF							
100 Pulses / KES 50	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept KES 50						ON				
Reject KES 50						OFF				
★ Accept KES 100							ON			
Reject KES 100							OFF			
★ Accept KES 200								ON		
Reject KES 200								OFF		
★ Accept KES 500									ON	
Reject KES 500									OFF	
★ Accept KES 1000										ON
Reject KES 1000										OFF

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

Note.2 Dip Switch 1 to 5 are only for Pulse mode.

Note.3 Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	ccTalk	ICT104U
BV1	KES 50	KES 50	KES 50	KES 50
BV2	KES 100	KES 100	KES 100	KES 100
BV3	KES 200	KES 200	KES 200	KES 200

Interface Bill value	Pulse	RS232 A0	ccTalk	ICT104U
BV4	KES 500	KES 500	KES 500	KES 500
BV5	KES 1000	KES 1000	KES 1000	KES 1000

L83-KES5(Pulse/RS232 A0/ccTalk/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
RS232 A0 Mode		ON	ON	OFF
★ Pulse Mode		ON	OFF	OFF
ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
RS232 A0 Mode		ON	ON	OFF
Pulse Mode		ON	OFF	OFF
★ ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
★ Reserved	OFF			
★ RS232 A0 Mode		ON	ON	OFF
Pulse Mode		ON	OFF	OFF
ICT104U Mode		ON	OFF	ON

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	Reserved
3	KES 50
4	KES 100
5	KES 200
6	KES 500
7	KES 1000
8	Reserved
9	Reserved

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
8-bit checksum	ON			
★ CRC 16-bit checksum	OFF			
ccTalk Mode		OFF	OFF	
ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
Encryption Mode				ON
★ Decrypt Mode				OFF

★ Manufacture setting

Note.3 Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.