

L83-RON8

L83-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ccTalk/Parallel A5)

Supported bill RON 1, 5, 10, 20, 50, 100, 200, 500
8bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / RON 1	OFF	OFF	OFF							
2 Pulses / RON 1	OFF	OFF	ON							
3 Pulses / RON 1	OFF	ON	OFF							
4 Pulses / RON 1	OFF	ON	ON							
5 Pulses / RON 1	ON	OFF	OFF							
10 Pulses / RON 1	ON	OFF	ON							
20 Pulses / RON 1	ON	ON	OFF							
100 Pulses / RON 1	ON	ON	ON							
Fast output Pulse Lo= 85ms Hi= 65ms				ON						
★ Slow output Pulse Lo=150ms Hi=100ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept RON 1						ON				
Reject RON 1						OFF				
★ Accept RON 5							ON			
Reject RON 5							OFF			
★ Accept RON 10 & 20								ON		
Reject RON 10 & 20								OFF		
★ Accept RON 50 & 100									ON	
Reject RON 50 & 100									OFF	
★ Accept RON 200 & 500										ON
Reject RON 200 & 500										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore CCTalk address to its default value of 40 and the encryption key to its default value of 123456.

L83-RON8(Pulse/ccTalk/Parallel A5)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
Parallel A5 Mode		ON	ON	
ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
★ CRC 16-bit checksum	ON			
8-bit checksum	OFF			
Pulse Mode		ON	OFF	
★ cctalk Interface		OFF	OFF	
Parallel A5 Mode		ON	ON	
ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

Note.3 : Turn this dip to with restart the bill acceptor will restore CCTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(Parallel A5)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
cctalk Interface		OFF	OFF	
★ Parallel A5 Mode		ON	ON	
ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ccTalk	Parallel A5
BV1	RON 1	RON 1	RON 1
BV2	RON 5	RON 5	RON 5
BV3	RON 10	RON 10	RON 10
BV4	RON 50	RON 50	RON 50
BV5	RON 100	RON 100	RON 100
BV6	RON 200	RON 200	RON 200
BV7	RON 500	RON 500	RON 500
BV8	RON 20	RON 20	RON 20