

L83-TND4

L83+ DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill TND 5, 10, 20, 50 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10				
★	1 Pulse / TND 5	OFF	OFF	OFF											
	2 Pulse / TND 5	OFF	OFF	ON											
	3 Pulse / TND 5	OFF	ON	OFF											
	4 Pulse / TND 5	OFF	ON	ON											
	5 Pulse / TND 5	ON	OFF	OFF											
	10 Pulse / TND 5	ON	OFF	ON											
	20 Pulse / TND 5	ON	ON	OFF											
	100 Pulse / TND 5	ON	ON	ON											
	Fast output Pulse Lo= 50ms Hi=100ms				ON										
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF										
	Inhibit level Active Low											ON			
★	Inhibit level Active High					OFF									
★	Accept TND 5											ON			
	Reject TND 5						OFF								
★	Accept TND 10												ON		
	Reject TND 10							OFF							
★	Accept TND 20													ON	
	Reject TND 20								OFF						
★	Accept TND 50														ON
	Reject TND 50									OFF					
	Reserved														
★	Reserved										OFF				

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

Currency Assign Data

Interface Bill value	Pulse	ICT104U	ICT104V	MDB
BV1	TND 5	TND 5	TND 5	TND 5
BV2	TND 10	TND 10	TND 10	TND 10
BV3	TND 20	TND 20	TND 20	TND 20
BV4	TND 50	TND 50	TND 50	TND 50

Appendix

L83-TND4(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 1000 Decimal Point Position (DPP) = 3	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
Pulse Mode				
ICT104U Mode				
★ MDB Mode				
ICT104V Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting