

# L83-UZS8

## L83 Option Switch Settings : 1(Pulse/RS232 A0/ccNet/ICT104U)

Supported bill UZS 1000, 2000, 5000, 10000, 20000, 50000, 100000, 200000 8bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / UZS 1000	OFF	OFF	OFF							
2 Pulses / UZS 1000	OFF	OFF	ON							
3 Pulses / UZS 1000	OFF	ON	OFF							
4 Pulses / UZS 1000	OFF	ON	ON							
5 Pulses / UZS 1000	ON	OFF	OFF							
10 Pulses / UZS 1000	ON	OFF	ON							
20 Pulses / UZS 1000	ON	ON	OFF							
100 Pulses / UZS 1000	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept UZS 1000 & 2000 & 5000						ON				
Reject UZS 1000 & 2000 & 5000						OFF				
★ Accept UZS 10000 & 20000 & 50000							ON			
Reject UZS 10000 & 20000 & 50000							OFF			
★ Accept UZS 100000								ON		
Reject UZS 100000								OFF		
★ Accept UZS 200000									ON	
Reject UZS 200000									OFF	
Simulation BillBox Has Been Removed										ON
★ Default										OFF

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

Note.2 Dip Switch 1 to 5 are only for Pulse mode.

Note.3 High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

### Currency Assign Data

Interface Bill value	Pulse	RS232 A0	ccNet	ICT104U
BV1				
BV2	UZS 1000	UZS 1000	UZS 1000	UZS 1000
BV3	UZS 5000	UZS 5000	UZS 5000	UZS 5000
BV4	UZS 10000	UZS 10000	UZS 10000	UZS 10000

Interface Bill value	Pulse	RS232 A0	ccNet	ICT104U
BV5	UZS 50000	UZS 50000	UZS 50000	UZS 50000
BV6	UZS 100000	UZS 100000	UZS 100000	UZS 100000
BV7	UZS 2000	UZS 2000	UZS 2000	UZS 2000
BV8	UZS 20000	UZS 20000	UZS 20000	UZS 20000
BV9	UZS 200000	UZS 200000	UZS 200000	UZS 200000

## Appendix

# L83-UZS8(Pulse/RS232 A0/ccNet/ICT104U)

## DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
RS232 A0 Mode		ON	ON	
★ Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
High Acceptance <small>(Note.3)</small>				ON
★ High Security <small>(Note.3)</small>				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
★ Reserved	OFF			
RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
★ ICT104U Mode		OFF	ON	
High Acceptance <small>(Note.3)</small>				ON
★ High Security <small>(Note.3)</small>				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
★ Reserved	OFF			
★ RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
High Acceptance <small>(Note.3)</small>				ON
★ High Security <small>(Note.3)</small>				OFF

★ Manufacture setting

### RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	UZS 1000
3	UZS 5000
4	UZS 10000
5	UZS 50000
6	UZS 100000
7	UZS 2000
8	UZS 20000
9	UZS 200000

## DIP SWITCHES SETTING : 2(ccNet)

FUNCTION	SW1	SW2	SW3	SW4
Baud rate 19200	ON			
★ Baud rate 9600	OFF			
RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
★ ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
High Acceptance <small>(Note.3)</small>				ON
★ High Security <small>(Note.3)</small>				OFF

★ Manufacture setting