

S7ER-SRD5 Option Switch Settings: (Pulse)

Supported bill SRD 5, 10, 20, 50, 100 5bills.

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
★ Reject SRD 5	ON															
★ Accept SRD 5	OFF															
★ Reject SRD 10		ON														
★ Accept SRD 10		OFF														
★ Reject SRD 20			ON													
★ Accept SRD 20			OFF													
★ Reject SRD 50				ON												
★ Accept SRD 50				OFF												
★ Reject SRD 100					ON											
★ Accept SRD 100					OFF											
★ Disable Bill Reject 4 Times BA Stop By 30 Sec					ON											
★ Enable Bill Reject 4 Times BA Stop By 30 Sec					OFF											
★ Stack Banknote when Power-up						ON										
★ Reject Banknote when Power-up						OFF										
★ Inhibit Active HIGH							ON									
★ Inhibit Active LOW							OFF									
★ Pulse Speed	100ms LO / 100ms HI						ON									
	50ms LO / 50ms HI						OFF									
★ Reserve								ON								
								OFF								
★ Reserve									ON							
									OFF							
★ Reserve										ON						
										OFF						
★ Credit-Pulse Normal HIGH											ON					
★ Credit-Pulse Normal LOW											OFF					
★ Pulse Mode												ON				
★ ICT104U Mode												OFF				
★ 1 pulse / SRD 5													OFF	OFF		
★ 2 pulses / SRD 5														OFF	ON	
★ 4 pulses / SRD 5														ON	OFF	
★ 5 pulses / SRD 5														ON	ON	

★ Manufacture setting

Note: After setting dip switch of the credit pulses, you should reset the bill acceptor again.

S7ER-SRD5 (ICT002)

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
★ Reject SRD 5	ON															
★ Accept SRD 5	OFF															
★ Reject SRD 10		ON														
★ Accept SRD 10		OFF														
★ Reject SRD 20			ON													
★ Accept SRD 20			OFF													
★ Reject SRD 50				ON												
★ Accept SRD 50				OFF												
★ Reject SRD 100					ON											
★ Accept SRD 100					OFF											
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
★ Stack Banknote when Power-up							ON									
★ Reject Banknote when Power-up							OFF									
★ Test Mode (No Communication)								ON								
★ Operation Mode								OFF								
★ Reserved									ON							
									OFF							
★ Reserved										ON						
										OFF						
★ Reserved											ON					
											OFF					
★ Reserved												ON				
												OFF				
★ Reserved													ON			
													OFF			
★ Pulse Mode														ON		
★ ICT002 Mode														OFF		
★ Reserved															ON	
★ Reserved															OFF	
★ Reserved																ON
★ Reserved																OFF

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note: 1.No RFID function.

Currency Assign Data

Interface Bill value	Pulse	ICT002
BV1		
BV2	SRD 5	SRD 5
BV3	SRD 10	SRD 10
BV4	SRD 20	SRD 20
BV5	SRD 100	SRD 100
BV6	SRD 50	SRD 50