

V7P-SAR4

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill SAR 1, 5, 10, 50 4bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject SAR 1	ON											
	Accept SAR 1	OFF											
★	Reject SAR 5		ON										
★	Accept SAR 5		OFF										
★	Reject SAR 10			ON									
★	Accept SAR 10			OFF									
★	Reject SAR 50				ON								
★	Accept SAR 50				OFF								
	Reserved				ON								
★	Reserved				OFF								
★	Reserved					ON							
★	Reserved					OFF							
★	Harness Disable						ON						
★	Harness Enable						OFF						
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
	Pulse Mode												
★	1 pulse / SAR 1								OFF	OFF			
	2 pulses / SAR 1								ON	OFF			
	4 pulses / SAR 1								OFF	ON			
	20 pulses / SAR 1								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

Note :

1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface Protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

V7P-SAR4(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse)

Currency Assign Data

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Bill value	Pulse	MDB	ICT104V	ICT104U
BV1	SAR 1	SAR 1	SAR 1	SAR 1
BV2	SAR 5	SAR 5	SAR 5	SAR 5
BV3	SAR 10	SAR 10	SAR 10	SAR 10
BV4	SAR 50	SAR 50	SAR 50	SAR 50

Interface Settings: 2(ICT104U/ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting