

V7P-TRY5

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill TRY 5, 10, 20, 50, 100 5bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject TRY 5	ON											
★	Accept TRY 5	OFF											
★	Reject TRY 10		ON										
★	Accept TRY 10		OFF										
★	Reject TRY 20			ON									
★	Accept TRY 20			OFF									
★	Reject TRY 50				ON								
★	Accept TRY 50				OFF								
★	Reject TRY 100					ON							
★	Accept TRY 100					OFF							
★	Reserved					ON							
★	Reserved					OFF							
★	Harness Disable						ON						
★	Harness Enable						OFF						
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / TRY 5								OFF	OFF			
★	5 pulses / TRY 5								ON	OFF			
★	10 pulses / TRY 5								OFF	ON			
★	25 pulses / TRY 5								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : 1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface Protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

V7P-TRY5(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface	Pulse	MDB	ICT104V	ICT104U
Bill value				
BV1	TRY 5	TRY 5	TRY 5	TRY 5
BV2	TRY 10	TRY 10	TRY 10	TRY 10
BV3	TRY 20	TRY 20	TRY 20	TRY 20
BV4	TRY 50	TRY 50	TRY 50	TRY 50
BV5	TRY100	TRY100	TRY100	TRY100

Interface Settings: 2(ICT104U/ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting