

XBA mini-AZN5

XBA mini Option Switch Settings: 1(Pulse/MDB/ccNet/RS232 A0/ICT104U)

Supported bill AZN 1, 5, 10, 20, 50 5bills.

XBA mini dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject AZN 1	ON											
★ Accept AZN 1	OFF											
★ Reject AZN 5		ON										
★ Accept AZN 5		OFF										
★ Reject AZN 10			ON									
★ Accept AZN 10			OFF									
★ Reject AZN 20				ON								
★ Accept AZN 20				OFF								
★ Reject AZN 50					ON							
★ Accept AZN 50					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec					ON							
★ Enable Bill Reject 4 Times BA Stop By 30 Sec					OFF							
★ Stack Banknote when Power-up						ON						
★ Reject Banknote when Power-up						OFF						
★ Reserved							ON					
★ Reserved							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ Reserved									ON			
★ Reserved									OFF			
★ Interface Timing Conversion		50ms LO / 50ms HI								OFF	OFF	
		60ms LO / 300ms HI								ON	OFF	
		30ms LO / 50ms HI								OFF	ON	
		150ms LO / 150ms HI								ON	ON	

Currency Assign Data

Interface Bill value	ICT104U	RS232 A0	ccNet	Pulse	MDB
BV1	AZN 1	AZN 1	AZN 1	AZN 1	AZN 1
BV2	AZN 5	AZN 5	AZN 5	AZN 5	AZN 5
BV3	AZN 10	AZN 10	AZN 10	AZN 10	AZN 10
BV4	AZN 20	AZN 20	AZN 20	AZN 20	AZN 20
BV5	AZN 50	AZN 50	AZN 50	AZN 50	AZN 50

XBA mini-AZN5(Pulse/MDB/ccNet/RS232 A0/ICT104U)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ 1 pulse / AZN 1			OFF	OFF
5 pulses / AZN 1			OFF	ON
10 pulses / AZN 1			ON	OFF
25 pulses / AZN 1			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
★ Reserved	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB Mode			OFF	OFF
ccNet Mode			OFF	ON
★ ICT104U Mode			ON	OFF
★ RS232 A0 Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(RS232 A0)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
★ Reserved	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB Mode			OFF	OFF
ccNet Mode			OFF	ON
★ ICT104U Mode			ON	OFF
★ RS232 A0 Mode			ON	ON

★ Manufacture setting

Note: (1) Calibration card is needed

(2) Dip switches 1 to 5 are only used for pulse protocol.

Interface Settings: 2(ccNet)

INTERFACE	SW1	SW2	SW3	SW4
★ 9600 Baud Rate	ON			
19200 Baud Rate	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB Mode			OFF	OFF
★ ccNet Mode			OFF	ON
★ ICT104U Mode			ON	OFF
★ RS232 A0 Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB Mode			OFF	OFF
★ ccNet Mode			OFF	ON
★ ICT104U Mode			ON	OFF
★ RS232 A0 Mode			ON	ON

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	AZN 1
2	Reserved
3	AZN 5
4	AZN 10
5	AZN 20
6	AZN 50