

XBA mini-GEL6

XBA mini Option Switch Settings: 1(Pulse/MDB/ccNet/RS232 A0/ICT104U)

Supported bill Lari 5, 10, 20, 50, 100, 200 6bills.

XBA mini dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Lari 5 & 10	ON											
★	Accept Lari 5 & 10	OFF											
★	Reject Lari 20		ON										
★	Accept Lari 20		OFF										
★	Reject Lari 50			ON									
★	Accept Lari 50			OFF									
★	Reject Lari 100				ON								
★	Accept Lari 100				OFF								
★	Reject Lari 200					ON							
★	Accept Lari 200					OFF							
★	Disable Bill Reject 4 Times BA Stop By 30 Sec					ON							
★	Enable Bill Reject 4 Times BA Stop By 30 Sec					OFF							
★	Stack Banknote when Power-up						ON						
★	Reject Banknote when Power-up						OFF						
★	Reserved							ON					
★	Reserved							OFF					
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	Reserved									ON			
★	Reserved									OFF			
★	Interface Timing Conversion	50ms LO / 50ms HI										OFF	OFF
		60ms LO / 300ms HI										ON	OFF
		30ms LO / 50ms HI										OFF	ON
		150ms LO / 150ms HI										ON	ON

Currency Assign Data

Interface Bill value	ccNet	RS232 A0	Pulse	MDB	ICT104U
BV1	Lari 5	Lari 5	Lari 5	Lari 5	Lari 5
BV2	Lari 10	Lari 10	Lari 10	Lari 10	Lari 10
BV3	Lari 20	Lari 20	Lari 20	Lari 20	Lari 20
BV4	Lari 50	Lari 50	Lari 50	Lari 50	Lari 50
BV5	Lari 100	Lari 100	Lari 100	Lari 100	Lari 100
BV6	Lari 200	Lari 200	Lari 200	Lari 200	Lari 200

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note : (1) Dip switches 1 to 5 are only used for pulse protocol.

(2) Calibration card is needed.

XBA mini-GEL6(Pulse/MDB/ccNet/RS232 A0/ICT104U)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / Lari 5			OFF	OFF
	2 pulses / Lari 5			OFF	ON
	5 pulses / Lari 5			ON	OFF
	20 pulses / Lari 5			ON	ON

★ Manufacture setting

Interface Settings: 2(ccNet)

	INTERFACE	SW1	SW2	SW3	SW4
★	9600 Baud Rate	ON			
	19200 Baud Rate	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	MDB Mode			OFF	OFF
★	ccNet Mode			OFF	ON
	ICT104U Mode			ON	OFF
	RS232 A0 Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	ccNet Mode			OFF	ON
★	ICT104U Mode			ON	OFF
	RS232 A0 Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	ccNet Mode			OFF	ON
	ICT104U Mode			ON	OFF
	RS232 A0 Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(RS232 A0)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	ccNet Mode			OFF	ON
	ICT104U Mode			ON	OFF
★	RS232 A0 Mode			ON	ON

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	Reserved
3	Lari 5
4	Lari 10
5	Lari 20
6	Lari 50
7	Lari 100
8	Lari 200
9	Reserved