

XBA mini-TRY5

XBA mini Option Switch Settings: 1(Pulse/MDB/ccNet/RS232 A0/ICT104U)

Supported bill Lira 5, 10, 20, 50, 100 5bills.

XBA mini dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject Lira 5	ON											
★ Accept Lira 5	OFF											
★ Reject Lira 10		ON										
★ Accept Lira 10		OFF										
★ Reject Lira 20			ON									
★ Accept Lira 20			OFF									
★ Reject Lira 50				ON								
★ Accept Lira 50				OFF								
★ Reject Lira 100					ON							
★ Accept Lira 100					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Stack Banknote when Power-up							ON					
★ Reject Banknote when Power-up							OFF					
★ Reserved								ON				
★ Reserved								OFF				
★ Inhibit Active High									ON			
★ Inhibit Active Low									OFF			
★ Reserved										ON		
★ Reserved										OFF		
★ Interface Timing Conversion	50ms LO / 50ms HI										OFF	OFF
	60ms LO / 300ms HI										ON	OFF
	30ms LO / 50ms HI										OFF	ON
	150ms LO / 150ms HI										ON	ON

Currency Assign Data

Interface	ccNet	RS232 A0	Pulse	MDB	ICT104U
BV1	Lira 5	Lira 5	Lira 5	Lira 5	Lira 5
BV2	Lira 10	Lira 10	Lira 10	Lira 10	Lira 10
BV3	Lira 20	Lira 20	Lira 20	Lira 20	Lira 20
BV4	Lira 50	Lira 50	Lira 50	Lira 50	Lira 50
BV5	Lira 100	Lira 100	Lira 100	Lira 100	Lira 100

XBA mini-TRY5(Pulse/MDB/ccNet/RS232 A0/ICT104U)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
Other Mode		OFF		
★ 1 pulse / Lari 5			OFF	OFF
5 pulses / Lari 5			OFF	ON
10 pulses / Lari 5			ON	OFF
25 pulses / Lari 5			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
★ Pulse Mode		ON		
Other Mode		OFF		
★ MDB Mode			OFF	OFF
ccNet Mode			OFF	ON
★ ICT104U Mode			ON	OFF
RS232 A0 Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(RS232 A0)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
★ Pulse Mode		ON		
Other Mode		OFF		
★ MDB Mode			OFF	OFF
ccNet Mode			OFF	ON
ICT104U Mode			ON	OFF
★ RS232 A0 Mode			ON	ON

★ Manufacture setting

Note:(1) Dip switches 1 to 5 are only used for pulse protocol.

(2) Calibration card is needed.

Interface Settings: 2(ccNet)

INTERFACE	SW1	SW2	SW3	SW4
★ 9600 Baud Rate	ON			
19200 Baud Rate	OFF			
Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB Mode			OFF	OFF
★ ccNet Mode			OFF	ON
ICT104U Mode			ON	OFF
RS232 A0 Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 1	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON		
Other Mode		OFF		
★ MDB Mode			OFF	OFF
ccNet Mode			OFF	ON
ICT104U Mode			ON	OFF
RS232 A0 Mode			ON	ON

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Lira 5
2	Lira 10
3	Lira 20
4	Lira 50
5	Lira 100