

XBA-CHF10(CHF4+EUR6) Option Switch Settings

Supported bill Fr 10, 20, 50, 100
 € 5, 10, 20, 50, 100, 200 10bills.


FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
★ Reject Fr 10 & 20 & 50	ON							
★ Accept Fr 10 & 20 & 50	OFF							
★ Reject Fr 100		ON						
★ Accept Fr 100		OFF						
★ Reject € 5 & 10			ON					
★ Accept € 5 & 10			OFF					
★ Reject € 20 & 50				ON				
★ Accept € 20 & 50				OFF				
★ Reject € 100(2019) & 200(2019)					ON			
★ Accept € 100(2019) & 200(2019)					OFF			
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON		
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF		
★ Stack Banknote when Power-up							ON	
★ Reject Banknote when Power-up							OFF	
★ Reserved								ON
★ Reserved								OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	JPSTD	ccTalk	Pulse	RS232 A0
BV1	Fr 10	Fr 10	Fr 10	Fr 10	Fr 10
BV2	Fr 20		Fr 20	Fr 20	Fr 20
BV3	Fr 50		Fr 50	Fr 50	Fr 50
BV4	Fr 100		Fr 100	Fr 100	Fr 100
BV5	€ 5		€ 5	€ 5	€ 5
BV6	€ 10		€ 10	€ 10	€ 10
BV7	€ 20		€ 20	€ 20	€ 20
BV8	€ 50		€ 50	€ 50	€ 50
BV9	€ 100		€ 100	€ 100	€ 100
BV10	€ 200		€ 200	€ 200	€ 200

This dip switch is located at the side of XBA.



RS232 A0 INFORMATION

BillType Data		BillType Data	
Code	Denomination	Code	Denomination
1	Fr 10	5	€ 5
2	Fr 20	6	€ 10
3	Fr 50	7	€ 20
4	Fr 100	8	€ 50
		9	€ 100
		10	€ 200

XBA-CHF10(Pulse/JPSTD/ccTalk/ICT104U/RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
Pulse Mode	Other Mode							
Inhibit Active HIGH	ON							
★ Inhibit Active LOW	OFF							
★ Reserved		ON						
★ Reserved		OFF						
★ 50ms LO/ 50ms HI			OFF	OFF				
★ 50ms LO/ 100ms HI			OFF	ON				
★ 65ms LO/ 75ms HI			ON	OFF				
★ 100ms LO/ 150ms HI			ON	ON				
★ Credit-Pulse Normal HIGH					ON			
★ Credit-Pulse Normal LOW					OFF			
★ Pulse Mode						ON		
★ Other Mode						OFF		
★ 1 pulse / € 5							OFF	OFF
★ 5 pulses / € 5							OFF	ON
★ 10 pulses / € 5							ON	OFF
★ 25 pulses / € 5							ON	ON

★ Manufacture setting

Note : 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

2. Turn this dip to with restart the bill acceptor will restore.

3. CCTalk address to its default value of 40 and the encryption key to its default value of 123456.

4. Calibration card is needed.

Table 1

	SW1	SW5
8-Bit Checksum	OFF	OFF
Restore mode(Note.2)	OFF	ON
CRC 16-Bit Decrypt Checksum	ON	OFF
CRC 16-Bit Encryption Checksum	ON	ON

This dip switch is located on the CPU board, remove the CPU board cover first.

