

A7/V7-HUF6

A7/V7 Option Switch Settings:1(Pulse/ccTalk)

Supported bill Ft 500, 1000, 2000, 5000, 10000, 20000 6bills.

A7/V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Ft 500	ON											
★	Accept Ft 500	OFF											
	Reject Ft 1000		ON										
★	Accept Ft 1000		OFF										
	Reject Ft 2000			ON									
★	Accept Ft 2000			OFF									
	Reject Ft 5000 & 1000				ON								
★	Accept Ft 5000 & 1000				OFF								
	Reject Ft 20000					ON							
★	Accept Ft 20000					OFF							
	Reserved					ON							
★	Reserved					OFF							
	Harness Disable						ON						
★	Harness Enable						OFF						
	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / Ft 500								OFF	OFF			
	5 pulses / Ft 500								ON	OFF			
	10 pulses / Ft 500								OFF	ON			
	20 pulses / Ft 500								ON	ON			
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A7/V7-HUF6(Pulse/ccTalk)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	ccTalk Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

Interface Settings: 2(ccTalk)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	ccTalk Interface Mode		OFF		
▲	ccTalk Parameters Restore Switch (Please see Note.3 for detail) (ccTalk only)			ON	
★	Reserved			OFF	
	Reserved				ON
★					OFF

★ Manufacture setting

▲ Note:3 cctalk Parameters Restore Switch

Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Currency Assign Data

Interface Bill value	ccTalk	Pulse
BV1	Ft 500	Ft 500
BV2	Ft 1000	Ft 1000
BV3	Ft 2000	Ft 2000
BV4	Ft 5000	Ft 5000
BV5	Ft 10000	Ft 10000
BV6	Ft 20000	Ft 20000