

## L70-COP6

### L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccTalk)

Supported bill COP 1000, 2000, 5000, 10000, 20000, 50000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / COP 1000	OFF	OFF	OFF							
	2 Pulses / COP 1000	OFF	OFF	ON							
	3 Pulses / COP 1000	OFF	ON	OFF							
	4 Pulses / COP 1000	OFF	ON	ON							
	5 Pulses / COP 1000	ON	OFF	OFF							
	10 Pulses / COP 1000	ON	OFF	ON							
	20 Pulses / COP 1000	ON	ON	OFF							
	100 Pulses / COP 1000	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept COP 1000					ON					
	Reject COP 1000					OFF					
★	Accept COP 2000						ON				
	Reject COP 2000						OFF				
★	Accept COP 5000 & 10000							ON			
	Reject COP 5000 & 10000							OFF			
★	Accept COP 20000								ON		
	Reject COP 20000								OFF		
★	Accept COP 50000									ON	
	Reject COP 50000									OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

## L70-COP6(Pulse/ICT104U/ccTalk)

### DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
	ICT104 Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Bill value	ICT104	Pulse	ccTalk
BV1	1000	1000	1000
BV2	2000	2000	2000
BV3	5000	5000	5000
BV4	10000	10000	10000
BV5	20000	20000	20000
BV6	50000	50000	50000

### DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
★	8-bit checksum	ON			
	CRC 16-bit checksum	OFF			
★	Pulse Mode		ON	OFF	
★	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
	ICT104 Interface		ON	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

### Decrypt MODE

	8-bit	CRC 16-bit
Encryption MODE	Reserved	ON
Decrypt MODE	Reserved	OFF

### DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★	ICT104 Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting