

L70-EUR2

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT106U/ICT104V/MDB)

Supported bill EUR 5, 10 2 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / EUR 5	OFF	OFF	OFF							
2 Pulses / EUR 5	OFF	OFF	ON							
3 Pulses / EUR 5	OFF	ON	OFF							
4 Pulses / EUR 5	OFF	ON	ON							
5 Pulses / EUR 5	ON	OFF	OFF							
10 Pulses / EUR 5	ON	OFF	ON							
20 Pulses / EUR 5	ON	ON	OFF							
100 Pulses / EUR 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept EUR 5						ON				
Reject EUR 5						OFF				
★ Accept EUR 10							ON			
Reject EUR 10							OFF			
★ Reserved								ON		
Reserved								OFF		
★ Reserved									ON	
Reserved									OFF	
★ Reserved										ON
Reserved										OFF

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

Note.2 Dip Switch 1 to 5 are only for Pulse mode.

L70-EUR2(Pulse/ICT106U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT106U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT106U	ICT104V
BV1	EUR 5	EUR 5	EUR 5	EUR 5
BV2	EUR 10	EUR 10	EUR 10	EUR 10

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT106U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
ICT106U Mode		OFF	OFF	
★ ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT106U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT106U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting