

L70-HUF6

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill Ft 500, 1000, 2000, 5000, 10000, 20000 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Ft 500	OFF	OFF	OFF							
2 Pulse / Ft 500	OFF	OFF	ON							
3 Pulse / Ft 500	OFF	ON	OFF							
4 Pulse / Ft 500	OFF	ON	ON							
5 Pulse / Ft 500	ON	OFF	OFF							
10 Pulse / Ft 500	ON	OFF	ON							
20 Pulse / Ft 500	ON	ON	OFF							
100 Pulse / Ft 500	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Ft 500						ON				
Reject Ft 500						OFF				
★ Accept Ft 1000							ON			
Reject Ft 1000							OFF			
★ Accept Ft 2000								ON		
Reject Ft 2000								OFF		
★ Accept Ft 5000 & 10000									ON	
Reject Ft 5000 & 10000									OFF	
★ Accept Ft 20000										ON
Reject Ft 20000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70-HUF6(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	Ft 500	Ft 500	Ft 500	Ft 500
BV2	Ft 1000	Ft 1000	Ft 1000	Ft 1000
BV3	Ft 2000	Ft 2000	Ft 2000	Ft 2000
BV4	Ft 5000	Ft 5000	Ft 5000	Ft 5000
BV5	Ft 10000	Ft 10000	Ft 10000	Ft 10000
BV6	Ft 20000	Ft 20000	Ft 20000	Ft 20000

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				
					OFF

★ Manufacture setting