

L70-MYR6

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT106U/ICT104V/MDB)

Supported bill M\$ 1, 5, 10, 20, 50, 100 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / M\$ 1	OFF	OFF	OFF							
	2 Pulses / M\$ 1	OFF	OFF	ON							
	3 Pulses / M\$ 1	OFF	ON	OFF							
	4 Pulses / M\$ 1	OFF	ON	ON							
	5 Pulses / M\$ 1	ON	OFF	OFF							
	10 Pulses / M\$ 1	ON	OFF	ON							
	20 Pulses / M\$ 1	ON	ON	OFF							
	100 Pulses / M\$ 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept M\$ 1				ON						
	Reject M\$ 1				OFF						
★	Accept M\$ 5				ON						
	Reject M\$ 5				OFF						
★	Accept M\$ 10				ON						
	Reject M\$ 10				OFF						
★	Accept M\$ 20				ON						
	Reject M\$ 20				OFF						
★	Accept M\$ 50 & 100				ON						
	Reject M\$ 50 & 100				OFF						

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

Note.2 Dip Switch 1 to 5 are only for Pulse mode.

L70-MYR6(Pulse/ICT106U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT106U	ICT104U
BV1	M\$ 1	M\$ 1	M\$ 1	M\$ 1
BV2				
BV3	M\$ 5	M\$ 5	M\$ 5	M\$ 5
BV4	M\$ 10	M\$ 10	M\$ 10	M\$ 10
BV5	M\$ 50	M\$ 50	M\$ 50	M\$ 50
BV6	M\$ 100	M\$ 100	M\$ 100	M\$ 100
BV7	M\$ 20	M\$ 20	M\$ 20	M\$ 20

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ICT106U Mode		OFF	OFF	
★	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT106U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting