

L70+/L70F-MMK6

L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccTalk)

Supported bill K 100, 200, 500, 1000, 5000, 10000 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / K 100	OFF	OFF	OFF							
2 Pulses / K 100	OFF	OFF	ON							
3 Pulses / K 100	OFF	ON	OFF							
4 Pulses / K 100	OFF	ON	ON							
5 Pulses / K 100	ON	OFF	OFF							
10 Pulses / K 100	ON	OFF	ON							
20 Pulses / K 100	ON	ON	OFF							
100 Pulses / K 100	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept K 100 & 200						ON				
Reject K 100 & 200						OFF				
★ Accept K 500 & 1000							ON			
Reject K 500 & 1000							OFF			
★ Accept K 5000								ON		
Reject K 5000								OFF		
★ Accept K 10000									ON	
Reject K 10000									OFF	
★ High Security										ON
High Acceptance <small>(Nota.4)</small>										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

(4) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

L70+/L70F-MMK6(Pulse/ICT104U/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
ICT104U Interface		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	ccTalk
BV1	100	100	100
BV2	200	200	200
BV3	500	500	500
BV4	1000	1000	1000
BV5	5000	5000	5000
BV6	10000	10000	10000

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
★ 8-bit checksum	ON			
CRC 16-bit checksum	OFF			
Pulse Mode		ON	OFF	
★ ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
ICT104U Interface		ON	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Decrypt MODE

	8-bit	CRC 16-bit
Encryption MODE	Reserved	ON
Decrypt MODE	Reserved	OFF

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★ ICT104U Interface		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting