

V7E/LX7-IDR7

V7E/LX7 Option Switch Settings: 1(Pulse/ICT106U/ICT104V/M.D.B)

Supported bill Rp 1000, 2000, 5000, 10000, 20000, 50000, 100000 7bills.

V7E/LX7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Rp 1000 & 2000	ON											
★	Accept Rp 1000 & 2000	OFF											
★	Reject Rp 5000 & 10000		ON										
★	Accept Rp 5000 & 10000		OFF										
★	Reject Rp 20000			ON									
★	Accept Rp 20000			OFF									
★	Reject Rp 50000				ON								
★	Accept Rp 50000				OFF								
★	Reject Rp 100000				ON								
★	Accept Rp 100000				OFF								
★	High Security					ON							
★	High Acceptance					OFF							
	Pulse Mode	Other Mode											
★	Harness Disable	BA stops working when fishing					ON						
★	Harness Enable	Normal					OFF						
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / Rp 1000								OFF	OFF			
	5 pulse / Rp 1000								ON	OFF			
	10 pulse / Rp 1000								OFF	ON			
	20 pulse / Rp 1000								ON	ON			
★	Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	Rp 1000	Rp 1000	Rp 1000
BV2	Rp 2000	Rp 2000	Rp 2000
BV3	Rp 5000	Rp 5000	Rp 5000
BV4	Rp 10000	Rp 10000	Rp 10000
BV5	Rp 20000	Rp 20000	Rp 20000
BV6	Rp 50000	Rp 50000	Rp 50000
BV7	Rp 100000	Rp 100000	Rp 100000

Appendix

V7E/LX7-IDR7(Pulse/ICT106U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
Scaling factor (SF) / Decimal place (DPP)	100 / 2	OFF	OFF	OFF
	10 / 2	OFF	OFF	ON
	1 / 2	OFF	ON	OFF
	100 / 1	OFF	ON	ON
	10 / 1	ON	OFF	OFF
	1 / 1	ON	OFF	ON
	10 / 0	ON	ON	OFF
	1 / 0	ON	ON	ON
Reserved				ON
Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(ICT106U)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT106U Interface		OFF	OFF	
ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT106U Interface		OFF	OFF	
ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
Pulse Mode		ON	OFF	
ICT106U Interface		OFF	OFF	
ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(MDB)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT106U Interface		OFF	OFF	
ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
Reserved				ON
				OFF

★ Manufacture setting