

V7E/LX7-JUD8

V7E/LX7 Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill JMD 50, 100, 500, 1000 4bills.
USD 1, 5, 10, 20 4bills.

V7E/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject JMD 50 & 100	ON											
★ Accept JMD 50 & 100	OFF											
★ Reject JMD 500 & 1000		ON										
★ Accept JMD 500 & 1000		OFF										
★ Reject USD 1 & 5			ON									
★ Accept USD 1 & 5			OFF									
★ Reject USD 10				ON								
★ Accept USD 10				OFF								
★ Reject USD 20					ON							
★ Accept USD 20					OFF							
★ Reserved					ON							
★ Reserved					OFF							
★ Pulse Mode	Other Mode											
★ Harness Disable	BA stopped working when fishing				ON							
★ Harness Enable	Normal				OFF							
★ Inhibit Active High					ON							
★ Inhibit Active Low					OFF							
★ 1 pulse / JMD 50					OFF	OFF						
2 pulses / JMD 50					ON	OFF						
5 pulses / JMD 50					OFF	ON						
10 pulses / JMD 50					ON	ON						
★ Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

(3) USD 1 display JMD 150 (Only for Pulse,MDB)

V7E/LX7-JUD8(Pulse/ICT104V/ICT104U/MDB)

DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	OFF	
ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

Interface Bill value	ICT104V	ICT104U	Pulse	MDB
BV1	JMD 50	JMD 50	JMD 50	JMD 50
BV2	JMD 100	JMD 100	JMD 100	JMD 100
BV3	JMD 500	JMD 500	JMD 500	JMD 500
BV4	JMD1000	JMD1000	JMD1000	JMD1000
BV5	USD 1	USD 1	USD 1	USD 1
BV6	USD 5	USD 5	USD 5	USD 5
BV7	USD 10	USD 10	USD 10	USD 10
BV8	USD 20	USD 20	USD 20	USD 20

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	OFF	
ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	OFF	
ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	OFF	
ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting