

EUR2

P70/P5 DIP SWITCHES SETTING : 1(Pulse/ccTalk)

Supported bill € 5, 10

2bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / € 5	OFF	OFF	OFF							
2 Pulses / € 5	OFF	OFF	ON							
3 Pulses / € 5	OFF	ON	OFF							
4 Pulses / € 5	OFF	ON	ON							
5 Pulses / € 5	ON	OFF	OFF							
10 Pulses / € 5	ON	OFF	ON							
20 Pulses / € 5	ON	ON	OFF							
100 Pulses / € 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept € 5						ON				
Reject € 5						OFF				
★ Accept € 10							ON			
Reject € 10							OFF			
Reserved								ON		
★ Reserved								OFF		
Reserved									ON	
★ Reserved									OFF	
Reserved										ON
★ Reserved										OFF

(★) Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

Currency Assign Data

Interface Bill value	ccTalk	Pulse
BV1	5	5
BV2	10	10

P70-EUR2/P5(Pulse/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ccTalk Protocol		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
★ Encryption Mode	ON			
Decrypt Mode	OFF			
Pulse Protocol		ON		
★ ccTalk Protocol		OFF		
ccTalk Parameters Reset			ON	
★ Keep ccTalk Parameters			OFF	
Manufacture Default				ON
★ System Default				OFF

(★) Manufacture setting

Note:(1) ccTalk Parameters Reset

Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

*This has to be done after finished calibration process.