



# JUD6

## P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill JMD 500, 1000

2bills.

USD 1, 5, 10, 20

4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / USD 1	OFF	OFF	OFF							
	2 Pulse / USD 1	OFF	OFF	ON							
	3 Pulse / USD 1	OFF	ON	OFF							
	4 Pulse / USD 1	OFF	ON	ON							
	5 Pulse / USD 1	ON	OFF	OFF							
	10 Pulse / USD 1	ON	OFF	ON							
	20 Pulse / USD 1	ON	ON	OFF							
	100 Pulse / USD 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept USD 1						ON				
	Reject USD 1						OFF				
★	Accept USD 5 & JMD 500							ON			
	Reject USD 5 & JMD 500							OFF			
★	Accept USD 10 & JMD 1000								ON		
	Reject USD 10 & JMD 1000								OFF		
★	Accept USD 20									ON	
	Reject USD 20									OFF	
★	Accept USD & JMD										ON
	Accept JMD Only										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Exchange Rate on USD to JMD is 1:100

For example, 5 USD = 500 JMD = 5 pulse and 10 USD = 1000 JMD = 10 pulses.

## DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

