

V7E+/LX7-SAR4

V7E+/LX7 Option Switch Settings: 1 (Pulse/ICT106U/MDB)

Supported bill SAR 1, 5, 10, 50 4 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
Reject SAR 1	ON											
Accept SAR 1	OFF											
Reject SAR 5		ON										
Accept SAR 5		OFF										
Reject SAR 10			ON									
Accept SAR 10			OFF									
Reject SAR 50				ON								
Accept SAR 50				OFF								
Reserved					ON							
Reserved					OFF							
Reserved						ON						
Reserved						OFF						
Pulse Mode	Other Mode											
Harness Disable	BA stops working when fishing					ON						
Harness Enable	Normal					OFF						
Inhibit Active High							ON					
Inhibit Active Low							OFF					
1 pulse / SAR 1								OFF	OFF			
5 pulses / SAR 1								ON	OFF			
10 pulses / SAR 1								OFF	ON			
20 pulses / SAR 1								ON	ON			
Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
	60ms LO / 300ms HI									ON	OFF	
	30ms LO / 50ms HI									OFF	ON	
	150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Note : (1) Default setting

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

V7E+/LX7-SAR4(Pulse/ICT106U/MDB)

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
Scaling factor(SF) / Decimal Point Position (DPP)	100 / 2	OFF	OFF	OFF
	10 / 2	OFF	OFF	ON
	1 / 2	OFF	ON	OFF
	100 / 1	OFF	ON	ON
	10 / 1	ON	OFF	OFF
	1 / 1	ON	OFF	ON
	10 / 0	ON	ON	OFF
	1 / 0	ON	ON	ON
Reserved				ON
Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
Pulse Normal High	ON			
Pulse Normal Low	OFF			
Pulse mode		ON	OFF	
ICT106U mode		OFF	ON	
MDB mode		ON	ON	
Reserved		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(MDB)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
	OFF			
Pulse mode		ON	OFF	
ICT106U mode		OFF	ON	
MDB mode		ON	ON	
Reserved		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(ICT106U)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
	OFF			
Pulse mode		ON	OFF	
ICT106U mode		OFF	ON	
MDB mode		ON	ON	
Reserved		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT106U
BV1	SAR 1	SAR 1	SAR 1
BV2	SAR 5	SAR 5	SAR 5
BV3	SAR 10	SAR 10	SAR 10
BV4			
BV5	SAR 50	SAR 50	SAR 50

◆ 1. Use 2nd 3rd dip of the internal dip-switch to change different interface protocol.

2. Remove the front cover and the dip-switch in on the CPU board.