

## V7E/LX7-THB4

### V7E/LX7 Option Switch Settings: 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill THB 20, 50, 100, 500

4bills.

V7E/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject THB 20	ON											
★ Accept THB 20	OFF											
★ Reject THB 50		ON										
★ Accept THB 50		OFF										
★ Reject THB 100			ON									
★ Accept THB 100			OFF									
★ Reject THB 500				ON								
★ Accept THB 500				OFF								
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Harness Disable						ON						
★ Harness Enable						OFF						
★ Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / THB 10								OFF	OFF			
5 pulses / THB 10								ON	OFF			
10 pulses / THB 10								OFF	ON			
20 pulses / THB 10								ON	ON			
★ Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

## V7E/LX7-THB4(Pulse/ICT104U/MDB/ICT104V)

### DIP SWITCHES SETTING : 3(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
ICT104V Interface		ON	ON	
MDB Interface		OFF	OFF	
★ Reserved				ON
				OFF

### Currency Assign Data

Interface Bill value	ICT104U	Pulse	MDB	ICT104V
BV1	THB 20	THB 20	THB 20	THB 20
BV2	THB 50	THB 50	THB 50	THB 50
BV3	THB 100	THB 100	THB 100	THB 100
BV4	THB 500	THB 500	THB 500	THB 500

### DIP SWITCHES SETTING : 3(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
ICT104V Interface		ON	ON	
MDB Interface		OFF	OFF	
★ Reserved				ON
				OFF

### DIP SWITCHES SETTING : 3(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
ICT104V Interface		ON	ON	
MDB Interface		OFF	OFF	
★ Reserved				ON
				OFF

### DIP SWITCHES SETTING : 3(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
ICT104V Interface		ON	ON	
MDB Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Note 1: Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

2: Remove the front cover and the dip-switch in on the CPU board.