

V7E+/LX7-TTD6

V7E+/LX7 Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill TTD 1, 5, 10, 20, 50, 100 6bills.

V7E/LX7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject TTD 1 & 5	ON											
★	Accept TTD 1 & 5	OFF											
	Reject TTD 10		ON										
★	Accept TTD 10		OFF										
	Reject TTD 20			ON									
★	Accept TTD 20			OFF									
	Reject TTD 50				ON								
★	Accept TTD 50				OFF								
	Reject TTD 100					ON							
★	Accept TTD 100					OFF							
	Reserved					ON							
★	Reserved					OFF							
	Pulse Mode	Other Mode											
	Harness Disable	BA stops working when fishing						ON					
★	Harness Enable	Normal						OFF					
	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / TTD 1								OFF	OFF			
	2 pulses / TTD 1								ON	OFF			
	4 pulses / TTD 1								OFF	ON			
	20 pulses / TTD 1								ON	ON			
★	Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

V7E+/LX7-TTD6(Pulse/ICT104V/ICT104U/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104U Mode		OFF	OFF	
	Reserved				ON
★	Reserved				OFF

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
BV1	TTD 1	TTD 1	TTD 1	TTD 1
BV2	TTD 5	TTD 5	TTD 5	TTD 5
BV3	TTD 10	TTD 10	TTD 10	TTD 10
BV4	TTD 20	TTD 20	TTD 20	TTD 20
BV5	TTD 100	TTD 100	TTD 100	TTD 100
BV6	TTD 50	TTD 50	TTD 50	TTD 50

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	ICT104U Mode		OFF	OFF	
	Rseerved				ON
★	Rseerved				OFF

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104U Mode		OFF	OFF	
	Rseerved				ON
★	Rseerved				OFF

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104U Mode		OFF	OFF	
	Rseerved				ON
★	Rseerved				OFF

★ Manufacture setting

Note 1. Default setting

2. Use both 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

3. Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)