

L77F&PL77-THB5

L77F&PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccNet)

Supported bill ₪ 20, 50,100,500,1000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / B 10	OFF	OFF	OFF							
	2 Pulse / B 10	OFF	OFF	ON							
	3 Pulse / B 10	OFF	ON	OFF							
	4 Pulse / B 10	OFF	ON	ON							
	5 Pulse / B 10	ON	OFF	OFF							
	10 Pulse / B 10	ON	OFF	ON							
	20 Pulse / B 10	ON	ON	OFF							
	100 Pulse / B 10	ON	ON	ON							
★	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
★	Inhibit level Active Low					ON					
	Inhibit level Active High					OFF					
★	Accept B 20 & 50						ON				
	Reject B 20 & 50						OFF				
★	Accept B 100							ON			
	Reject B 100							OFF			
★	Accept B 500								ON		
	Reject B 500								OFF		
★	Accept B 1000									ON	
	Reject B 1000									OFF	
★	High Security										ON
	High Acceptance <small>(Nota.4)</small>										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only for Pulse model.

(3) Special Pulse : ₪20->1 Pulse · ₪50->2 Pulse · ₪100->3 Pulse · ₪500->4 Pulse · ₪1000->5 Pulse.

Normal Pulse : ₪20->2 Pulse · ₪50->5 Pulse · ₪100->10 Pulse · ₪500->50 Pulse · ₪1000->100 Pulse.

(4) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

L77F&PL77-THB5(Pulse/ICT104U/ccNet)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	ICT104U Mode		ON	ON	
★	Pulse Mode		ON	OFF	
	ccNet Mode		OFF	OFF	
	Reserved		OFF	ON	
	Special Pulse (Note.3)				ON
★	Normal Pulse				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccNet)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	ICT104U Mode		ON	ON	
	Pulse Mode		ON	OFF	
★	ccNet Mode		OFF	OFF	
	Reserved		OFF	ON	
					ON
★	Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	ICT104U Mode		ON	ON	
	Pulse Mode		ON	OFF	
	ccNet Mode		OFF	OFF	
	Reserved		OFF	ON	
					ON
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse	ccNet
BV1	₪ 20	₪ 20	₪ 20
BV2	₪ 50	₪ 50	₪ 50
BV3	₪ 100	₪ 100	₪ 100
BV4	₪ 500	₪ 500	₪ 500
BV5	₪ 1000	₪ 1000	₪ 1000