

L77F/PL77-INR8

L77F/PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill Rs 5, 10, 20, 50, 100, 200, 500, 2000 8bills.

With stacker : Rs 5, 10, 20, 50, 100, 200, 500 7bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Rs 5 & 10 (Note.2)	OFF	OFF	OFF							
2 Pulse / Rs 5 & 10 (Note.2)	OFF	OFF	ON							
3 Pulse / Rs 5 & 10 (Note.2)	OFF	ON	OFF							
4 Pulse / Rs 5 & 10 (Note.2)	OFF	ON	ON							
5 Pulse / Rs 5 & 10 (Note.2)	ON	OFF	OFF							
10 Pulse / Rs 5 & 10 (Note.2)	ON	OFF	ON							
20 Pulse / Rs 5 & 10 (Note.2)	ON	ON	OFF							
100 Pulse / Rs 5 & 10 (Note.2)	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Rs 5 (Note.2)						ON				
Reject Rs 5 (Note.2)						OFF				
★ Accept Rs 10 & 20 & 50							ON			
Reject Rs 10 & 20 & 50							OFF			
★ Accept Rs 100 & 200 & 500								ON		
Reject Rs 100 & 200 & 500								OFF		
★ Accept Rs 2000									ON	
Reject Rs 2000									OFF	
High Security Mode										ON
★ Medium Security Mode										OFF

★ Manufacture setting

Note : (1) Please reset the bill acceptor after set the dip switch.

(2) ** Pulse Mode:

When Dip 6 is OFF,One Pulse per INR 10.

When Dip 6 is ON,One Pulse per INR 5.

** MDB Mode:

When Dip 6 is ON,Reject INR 2000.

When Dip 6 is OFF,Accept INR 2000.

L77F/PL77-INR8 (Pulse/ICT104U/MDB/ICT104V)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface	ICT104U	Pulse		MDB	
Bill value	ICT104V	When Dip 6 is OFF	When Dip 6 is ON	When Dip 6 is OFF	When Dip 6 is ON
BV1	Rs 5		Rs 5	Rs 10	Rs 5
BV2	Rs 10	Rs 10	Rs 10	Rs 20	Rs 10
BV3	Rs 20	Rs 20	Rs 20	Rs 50	Rs 20
BV4	Rs 50	Rs 50	Rs 50	Rs 100	Rs 50
BV5	Rs 100	Rs 100	Rs 100	Rs 200	Rs 100
BV6	Rs 500	Rs 200	Rs 200	Rs 500	Rs 200
BV7		Rs 500	Rs 500		Rs 500
BV8	Rs 2000			Rs 2000	
BV9	Rs 200	Rs 2000	Rs 2000		

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting