

L77F-PHP6

L77F DIP SWITCHES SETTING : 1(Pulse/ccTalk/ICT104)

Supported bill ₱ 20, 50, 100, 200, 500, 1000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / ₱ 10	OFF	OFF	OFF							
	2 Pulse / ₱ 10	OFF	OFF	ON							
	3 Pulse / ₱ 10	OFF	ON	OFF							
	4 Pulse / ₱ 10	OFF	ON	ON							
	5 Pulse / ₱ 10	ON	OFF	OFF							
	10 Pulse / ₱ 10	ON	OFF	ON							
	20 Pulse / ₱ 10	ON	ON	OFF							
	100 Pulse / ₱ 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
★	Inhibit level Active Low (Note.4)				ON						
	Inhibit level Active High				OFF						
★	Accept ₱ 20				ON						
	Reject ₱ 20				OFF						
★	Accept ₱ 50				ON						
	Reject ₱ 50				OFF						
★	Accept ₱ 100 & 200				ON						
	Reject ₱ 100 & 200				OFF						
★	Accept ₱ 500				ON						
	Reject ₱ 500				OFF						
★	Accept ₱ 1000				ON						
	Reject ₱ 1000				OFF						

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

(4) External motor Command. (ICT & ccTalk ONLY)

ON : Motor Command.

OFF : Reserved.

L77F-PHP6(Pulse/ccTalk/ICT104)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ICT104 Mode		ON	ON	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
	Pulse Mode		ON	OFF	
★	ccTalk Interface		OFF	OFF	
	ICT104 Mode		ON	ON	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(ICT104)

	FUNCTION	SW1	SW2	SW3	SW4
★	Forth ONLY	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
★	ICT104 Mode		ON	ON	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	ccTalk	Pulse
BV1	₱ 20	₱ 20	₱ 20
BV2	₱ 50	₱ 50	₱ 50
BV3	₱ 100	₱ 100	₱ 100
BV4	₱ 500	₱ 200	₱ 200
BV5	₱ 1000	₱ 500	₱ 500
BV6	₱ 200	₱ 1000	₱ 1000