

L77F/PL77-GEL6

L77F/PL77 Option Switch Settings : 1(Pulse/ICT104U/MDB/ccTalk)

Supported bill Lari 5, 10, 20, 50, 100, 200 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Lari 5	OFF	OFF	OFF							
	2 Pulses / Lari 5	OFF	OFF	ON							
	3 Pulses / Lari 5	OFF	ON	OFF							
	4 Pulses / Lari 5	OFF	ON	ON							
	5 Pulses / Lari 5	ON	OFF	OFF							
	10 Pulses / Lari 5	ON	OFF	ON							
	20 Pulses / Lari 5	ON	ON	OFF							
	100 Pulses / Lari 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept Lari 5 & 10				ON						
	Reject Lari 5 & 10				OFF						
★	Accept Lari 20 & 50				ON						
	Reject Lari 20 & 50				OFF						
★	Accept Lari 100				ON						
	Reject Lari 100				OFF						
★	Accept Lari 200				ON						
	Reject Lari 200				OFF						
★	Reserved				ON						
	Reserved				OFF						

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.
 (2)Dip switches 1 to 5 are only used for pulse protocol.
 (3)Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L77F/PL77-GEL6(Pulse/ICT104U/MDB/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	MDB Mode		ON	ON	OFF
★	Pulse Mode		ON	OFF	OFF
	ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	MDB Mode		ON	ON	OFF
	Pulse Mode		ON	OFF	OFF
★	ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP)= 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP)= 0	OFF			
★	MDB Mode		ON	ON	OFF
	Pulse Mode		ON	OFF	OFF
	ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
★	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Nota.3 for Detail)		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse	ccTalk	ICT104U
BV3	Lari 5(O)	Lari 5(O)	Lari 5(O)	Lari 5(O)
BV4	Lari 5(N)	Lari 5(N)	Lari 5(N)	Lari 5(N)
BV5	Lari 10(O)	Lari 10(O)	Lari 10(O)	Lari 10(O)
BV6	Lari 10(N)	Lari 10(N)	Lari 10(N)	Lari 10(N)
BV7	Lari 20(O)	Lari 20(O)	Lari 20(O)	Lari 20(O)
BV8	Lari 20(N)	Lari 20(N)	Lari 20(N)	Lari 20(N)
BV9	Lari 50(O)	Lari 50(O)	Lari 50(O)	Lari 50(O)
BV10	Lari 50(N)	Lari 50(N)	Lari 50(N)	Lari 50(N)
BV11	Lari 100(O)	Lari 100(O)	Lari 100(O)	Lari 100(O)
BV12	Lari 100(N)	Lari 100(N)	Lari 100(N)	Lari 100(N)
BV13	Lari 200	Lari 200	Lari 200	Lari 200