

# L77F&PL77-TRY6

## L77F&PL77 DIP SWITCHES SETTING : 1(Pulse/ICT106U/ICT104V/ccNet)

Supported bill TRY 5, 10, 20, 50, 100, 200 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / TRY 5	OFF	OFF	OFF							
	2 Pulse / TRY 5	OFF	OFF	ON							
	3 Pulse / TRY 5	OFF	ON	OFF							
	4 Pulse / TRY 5	OFF	ON	ON							
	5 Pulse / TRY 5	ON	OFF	OFF							
	10 Pulse / TRY 5	ON	OFF	ON							
	20 Pulse / TRY 5	ON	ON	OFF							
	100 Pulse / TRY 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept TRY 5						ON				
	Reject TRY 5						OFF				
★	Accept TRY 10							ON			
	Reject TRY 10							OFF			
★	Accept TRY 20								ON		
	Reject TRY 20								OFF		
★	Accept TRY 50									ON	
	Reject TRY 50									OFF	
★	Accept TRY 100 & 200										ON
	Reject TRY 100 & 200										OFF

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

Note.2 Dip Switch 1 to 5 are only for Pulse mode.

# L77F&PL77-TRY6(Pulse/ICT106U/ICT104V/ccNet)

## DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	ccNet Mode		ON	ON	
★	Pulse Mode		ON	OFF	
	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(ICT106U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	ccNet Mode		ON	ON	
	Pulse Mode		ON	OFF	
★	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	ccNet Mode		ON	ON	
	Pulse Mode		ON	OFF	
★	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(ccNet)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	ccNet Mode		ON	ON	
	Pulse Mode		ON	OFF	
	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	Pulse	ICT106U	ICT104V	ccNet
BV1	TRY 5	TRY 5	TRY 5	TRY 5
BV2	TRY 10	TRY 10	TRY 10	TRY 10
BV3	TRY 20	TRY 20	TRY 20	TRY 20
BV4	TRY 50	TRY 50	TRY 50	TRY 50
BV5	TRY 100	TRY 100	TRY 100	TRY 100
BV6	TRY 200	TRY 200	TRY 200	TRY 200