

## NBA-SGD5

### NBA DIP SWITCH SETTINGS: 1 (Pulse/ICT004U/RS232 A0/RS232 A1/ccTalk)

Supported bill S\$ 2, 5, 10, 50, 100 5 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
⊙	Accept S\$ 2	ON							
	Reject S\$ 2	OFF							
⊙	Accept S\$ 5		ON						
	Reject S\$ 5		OFF						
⊙	Accept S\$ 10			ON					
	Reject S\$ 10			OFF					
⊙	Accept S\$ 50				ON				
	Reject S\$ 50				OFF				
⊙	Accept S\$ 100					ON			
	Reject S\$ 100					OFF			
⊙	Reserved						ON		
	Reserved						OFF		
▲ ⊙	Harness Enable							ON	
▲	Harness Disable							OFF	
▲ ⊙	Inhibit Active High								ON
▲	Inhibit Active Low								OFF

### DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
▲ ⊙	1 pulse / S\$ 1	OFF	OFF						
▲	2 pulses / S\$ 1	ON	OFF						
▲	4 pulses / S\$ 1	OFF	ON						
▲	10 pulses / S\$ 1	ON	ON						
▲ ⊙	Pulse Speed	50ms on / 50ms off		OFF	OFF				
▲		30ms on / 50ms off		ON	OFF				
▲		60ms on / 300ms off		OFF	ON				
▲		150ms on / 150ms off		ON	ON				
⊙	ccTalk Mode					OFF	OFF		
	ICT004U Mode					ON	OFF		
	RS232 A1 Mode					OFF	ON		
	RS232 A0 Mode					ON	ON		
	ccTalk Parameters Restore Switch Please see "Note.3" for detail							ON	
⊙	ccTalk Interface							OFF	
⊙	Encryption Mode(for ccTalk Mode use only)								ON
	Decrypt Mode								OFF

(⊙) Factory setting. (▲) For pulse interface only.

Note: (3) Turn this dip to with restart the bill acceptor will restore

CCTalk address to its default value of 40 and the encryption key to its default value of 123456.

## NBA-SGD5(Pulse/ICT004U/RS232 A0/RS232 A1/ccTalk)

### DIP SWITCHES SETTING : 3

	FUNCTION	SW1	SW2	SW3	SW4
▲ ⊙	Credit-Pulse Normal HIGH	ON			
▲	Credit-Pulse Normal LOW	OFF			
▲ ⊙	Pulse Mode		ON		
	Others Mode (Note.2)		OFF		
	RFID function Enable			ON	
⊙	RFID function Disable			OFF	
	Optical anti-fishing malfunction, BA will be still in working order				ON
⊙	BA will stop work when it acknowledges optical anti-fishing malfunction.				OFF

(⊙) Factory setting.

(▲) For pulse interface only.

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW2 (front panel right block) Dip Switch 1 to 4 are only for Pulse mode.  
if set to others mode, SW2 Dip Switch 1 to 4 can change to different interface.

(3) Turn this dip to with restart the bill acceptor will restore  
CCTalk address to its default value of 40 and the encryption key to its  
default value of 123456.

(4) RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	S\$ 2
2	S\$ 5
3	S\$ 10
4	S\$ 50
5	S\$ 100
6	Reserved
7	Reserved
8	Reserved
9	Reserved