

XBA mini-CAD5

XBA mini Option Switch Settings: 1(Pulse/MDB/JPSTD/ICT104V/ICT104U)

Supported bill CAD 5, 10, 20, 50, 100 5bills.

XBA mini dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject CAD 5	ON											
★	Accept CAD 5	OFF											
★	Reject CAD 10		ON										
★	Accept CAD 10		OFF										
★	Reject CAD 20			ON									
★	Accept CAD 20			OFF									
★	Reject CAD 50				ON								
★	Accept CAD 50				OFF								
★	Reject CAD 100					ON							
★	Accept CAD 100					OFF							
★	Disable Bill Reject 4 Times BA Stop By 30 Sec					ON							
★	Enable Bill Reject 4 Times BA Stop By 30 Sec					OFF							
★	Colorful light						OFF	OFF					
★	The green light flashes						OFF	ON					
	Reserved						ON	OFF					
	No light						ON	ON					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
	Reserved									ON			
★	Reserved									OFF			
★	Interface Timing Conversion	5ms LO / 5ms HI									OFF	OFF	
		5ms LO / 10ms HI									ON	OFF	
		10ms LO / 10ms HI									OFF	ON	
		20ms LO / 20ms HI									ON	ON	

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note : (1) Calibration card is needed.

XBA mini-CAD5(Pulse/MDB/JPSTD/ICT104V/ICT104U)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / CAD 1			OFF	OFF
	2 pulses / CAD 1			OFF	ON
	4 pulses / CAD 1			ON	OFF
	20 pulses / CAD 1			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
★	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Connect with coin changer	ON			
	Connect with ICT JPSTD converter board	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
	ICT104U Mode			ON	OFF
★	ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface	JPSTD	ICT104U	ICT104V	Pulse	MDB
Bill value					
BV1	CAD 5	CAD 5	CAD 5	CAD 5	CAD 5
BV2		CAD 10	CAD 10	CAD 10	CAD 10
BV3		CAD 20	CAD 20	CAD 20	CAD 20
BV4		CAD 50	CAD 50	CAD 50	CAD 50
BV5		CAD 100	CAD 100	CAD 100	CAD 100