

XBA mini-VND6

XBA mini Option Switch Settings: 1(Pulse/MDB/JPSTD/ICT104U/ICT-BC)

Supported bill VND 1000, 2000, 5000, 10000, 20000, 50000, 6bills.

XBA mini dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject VND 1000 & 2000 (Note,4)	ON											
★	Accept VND 1000 & 2000 (Note,4)	OFF											
★	VND 5000 & 10000 & 20000 & 50000	OFF	OFF	OFF									
	VND 5000 & 10000 & 20000	OFF	OFF	ON									
	VND 5000 & 10000	OFF	ON	OFF									
	VND 10000 & 20000 & 50000	OFF	ON	ON									
	VND 5000	ON	OFF	OFF									
	VND 10000	ON	OFF	ON									
	VND 20000	ON	ON	OFF									
	VND 50000	ON	ON	ON									
	Don't Detect Stacker(Disable EX account)				ON								
★	Detect Stacker(Enable EX account)				OFF								
★	Disable Bill Reject 4 Times BA Stop By 30 Sec				ON								
★	Enable Bill Reject 4 Times BA Stop By 30 Sec				OFF								
	Stack Banknote when Power-up				ON								
★	Reject Banknote when Power-up				OFF								
	High Acceptance (Note,6)				ON								
★	High Security				OFF								
	Pulse Mode												
	MDB Mode												
	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
	Reserved								ON				
★	Reserved									OFF			
★	Interface Timing Conversion												
	50ms LO / 50ms HI									OFF		OFF	
	60ms LO / 300ms HI									ON		OFF	
	30ms LO / 50ms HI									OFF		ON	
	150ms LO / 150ms HI									ON		ON	

★ Manufacture setting

XBA mini-VND6(Pulse/MDB/JPSTD/ICT104U/ICT-BC)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / VND 1000 & 5000	(Note,4)		OFF	OFF
	5 pulses / VND 1000 & 5000	(Note,4)		OFF	ON
	10 pulses / VND 1000 & 5000	(Note,4)		ON	OFF
	20 pulses / VND 1000 & 5000	(Note,4)		ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB Mode (Note,7)			OFF	OFF
	JPSTD Mode			OFF	ON
	ICT104U Mode			ON	OFF
	ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(Other)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
	ICT104U Mode			ON	OFF
	ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD	ICT104U	ICT-BC	MDB	Pulse	
					When Dip 1 is OFF	When Dip 1 is ON
BV1	1000	1000	1000	1000	1000	5000
BV2		2000	2000	2000	2000	10000
BV3		5000	5000	5000	5000	20000
BV4		10000	10000	10000	10000	50000
BV5		20000	20000	20000	20000	
BV6		50000	50000	50000	50000	

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Dip switches 1 to 5 are only used for pulse protocol.

(4) Pulse Mode : When Dip 1 is OFF, One Pulse per VND 1000.
When Dip 1 is ON , One Pulse per VND 5000.

(5) Calibration card is needed.

(6) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

(7) Scaling Factor (SF) = 1, Decimal Point Position (DPP) = 0 .