

XBA mini-VND6

XBA mini Option Switch Settings: 1(Pulse/MDB/JPSTD/ICT104U/ICT104V)

Supported bill VND 1000, 2000, 5000, 10000, 20000, 50000 6bills.

XBA mini dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject VND 1000 & 2000 (Note.4)	ON											
★	Accept VND 1000 & 2000 (Note.4)	OFF											
★	VND 5000 & 10000 & 20000 & 50000		OFF	OFF	OFF								
	VND 5000 & 10000 & 20000		OFF	OFF	ON								
	VND 5000 & 10000		OFF	ON	OFF								
	VND 10000 & 20000 & 50000		OFF	ON	ON								
	VND 5000		ON	OFF	OFF								
	VND 10000		ON	OFF	ON								
	VND 20000		ON	ON	OFF								
	VND 50000		ON	ON	ON								
★	Don't Detect Stacker (Disable EX account)					ON							
★	Detect Stacker (Enable EX account)					OFF							
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★	Stack Banknote when Power-up							ON					
★	Reject Banknote when Power-up							OFF					
★	High Acceptance (Note.6)								ON				
★	High Security								OFF				
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	DIV 100 (MDB Mode)									ON			
★	Normal (MDB Mode)									OFF			
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Dip switches 1 to 5 are only used for pulse protocol.

(4) Pulse Mode : When Dip 1 is OFF, One Pulse per VND 1000.

When Dip 1 is ON , One Pulse per VND 5000.

(5) Calibrate card.

(6) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

XBA mini-VND6(Pulse/MDB/JPSTD/ICT104V/ICT104U)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / VND 1000 & 5000 (Note.4)			OFF	OFF
	5 pulses / VND 1000 & 5000 (Note.4)			OFF	ON
	10 pulses / VND 1000 & 5000 (Note.4)			ON	OFF
	20 pulses / VND 1000 & 5000 (Note.4)			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(Other)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Connect with coin changer	ON			
	Connect with ICT VCCS Converter board	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
	ICT104U Mode			ON	OFF
★	ICT104V Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD	ICT104U	ICT104V	MDB	Pulse	
					When Dip 1 is OFF	When Dip 1 is ON
BV1	1000	1000	1000	1000	1000	5000
BV2		2000	2000	2000	2000	10000
BV3		5000	5000	5000	5000	20000
BV4		10000	10000	10000	10000	50000
BV5		20000	20000	20000	20000	
BV6		50000	50000	50000	50000	