

A7/V7-TRY5

A7/V7 Option Switch Settings:1(Pulse/ccTalk)

Supported bill TRY 5, 10, 20, 50, 100 5bills.

A7/V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject TRY 5	ON											
	Accept TRY 5	OFF											
★	Reject TRY 10		ON										
	Accept TRY 10		OFF										
★	Reject TRY 20			ON									
	Accept TRY 20			OFF									
★	Reject TRY 50				ON								
	Accept TRY 50				OFF								
★	Reject TRY 100					ON							
	Accept TRY 100					OFF							
★	Reserved					ON							
	Reserved					OFF							
★	Harness Disable						ON						
	Harness Enable						OFF						
★	Inhibit Active High							ON					
	Inhibit Active Low							OFF					
★	1 pulse / TRY 5								OFF	OFF			
	5 pulses / TRY 5								ON	OFF			
	10 pulses / TRY 5								OFF	ON			
	20 pulses / TRY 5								ON	ON			
★	Pulse Speed	50ms LO / 50ms HI								OFF		OFF	
		60ms LO / 300ms HI								ON		OFF	
		30ms LO / 50ms HI								OFF		ON	
		150ms LO / 150ms HI								ON		ON	

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A7/V7-TRY5(Pulse/ccTalk)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	ccTalk Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

Interface Settings: 3(ccTalk)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON		
★	ccTalk Interface		OFF		
▲	cctalk Parameters Restore Switch			ON	
				OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

▲ Put this switch to on and reset power will restore the cctalk address to its default value of 40, and the encryption key to its default value of 123456. This needs to be done after each White card Calibration.

Currency Assign Data

Interface Bill value	ccTalk	Pulse
BV1	TRY 5	TRY 5
BV2	TRY 10	TRY 10
BV3	TRY 20	TRY 20
BV4	TRY 50	TRY 50
BV5	TRY 100	TRY 100