

## TAO-A-USD6

### TAO-A Option Switch Settings: 1(Pulse+NISR+ICT002U+5V Enable+Out of Service)

Supported bill USD 1, 5, 10, 20, 50, 100 6 bills.

TAO-A dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject USD 1	ON											
★	Accept USD 1	OFF											
	Reject USD 5		ON										
★	Accept USD 5		OFF										
	Reject USD 10			ON									
★	Accept USD 10			OFF									
	Reject USD 20				ON								
★	Accept USD 20				OFF								
	Reject USD 50 & 100					ON							
★	Accept USD 50 & 100					OFF							
	Auto Detection SEND Signal (NISR Mode only)						ON						
★	Normal High SEND Signal (NISR Mode only)						OFF						
	<b>Pulse Mode</b>	<b>Other Mode</b>											
	Harness Disable	BA stops working when fishing						ON					
★	Harness Enable	Normal						OFF					
	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / USD 1							OFF	OFF				
	2 pulse / USD 1							ON	OFF				
	4 pulse / USD 1							OFF	ON				
	20 pulse / USD 1							ON	ON				
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) Pulse mode has out of service function.

## TAO-A-USD6(Pulse+NISR+ICT002U+5V Enable+Out of Service)

### Interface Settings: 2(ICT)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	ICT002U Mode		ON	ON	
	NISR Mode		OFF	ON	
	Pulse Mode		ON	OFF	
	5V Enable Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

### Interface Settings: 2(NISR)

	INTERFACE	SW1	SW2	SW3	SW4
	No ERROR CODE	ON			
★	Send ERROR CODE	OFF			
	ICT002U Mode		ON	ON	
★	NISR Mode		OFF	ON	
	Pulse Mode		ON	OFF	
	5V Enable Mode		OFF	OFF	
	Standard Mode				ON
★	Customized Mode				OFF

★ Manufacture setting

### Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
	ICT002U Mode		ON	ON	
	NISR Mode		OFF	ON	
★	Pulse Mode		ON	OFF	
	5V Enable Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	Pulse	ICT	NISR
BV1	USD 1	USD 1	USD 1
BV2	USD 5	USD 5	
BV3	USD 10	USD 10	USD 5
BV4	USD 20	USD 20	USD 10
BV5	USD 50	USD 50	USD 20
BV6	USD 100	USD 100	USD 50
BV7			USD 100

### Interface Settings: 2(5V Enable)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
	ICT002U Mode		ON	ON	
	NISR Mode		OFF	ON	
	Pulse Mode		ON	OFF	
★	5V Enable Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting